

Opus

1.2-beta-8-g4507637

Generated by Doxygen 1.8.1.2

Thu May 25 2017 17:08:32

Contents

1	Opus	1
2	Module Index	3
2.1	Modules	3
3	File Index	5
3.1	File List	5
4	Module Documentation	7
4.1	Opus Encoder	7
4.1.1	Detailed Description	7
4.1.2	Typedef Documentation	9
4.1.2.1	OpusEncoder	9
4.1.3	Function Documentation	9
4.1.3.1	opus_encode	9
4.1.3.2	opus_encode_float	10
4.1.3.3	opus_encoder_create	10
4.1.3.4	opus_encoder_ctl	11
4.1.3.5	opus_encoder_destroy	11
4.1.3.6	opus_encoder_get_size	11
4.1.3.7	opus_encoder_init	12
4.2	Opus Decoder	13
4.2.1	Detailed Description	14
4.2.2	Typedef Documentation	15
4.2.2.1	OpusDecoder	15
4.2.3	Function Documentation	15
4.2.3.1	opus_decode	15
4.2.3.2	opus_decode_float	15
4.2.3.3	opus_decoder_create	16

4.2.3.4	opus_decoder_ctl	16
4.2.3.5	opus_decoder_destroy	16
4.2.3.6	opus_decoder_get_nb_samples	17
4.2.3.7	opus_decoder_get_size	17
4.2.3.8	opus_decoder_init	17
4.2.3.9	opus_packet_get_bandwidth	18
4.2.3.10	opus_packet_get_nb_channels	18
4.2.3.11	opus_packet_get_nb_frames	18
4.2.3.12	opus_packet_get_nb_samples	19
4.2.3.13	opus_packet_get_samples_per_frame	19
4.2.3.14	opus_packet_parse	19
4.2.3.15	opus_pcm_soft_clip	20
4.3	Repacketizer	21
4.3.1	Detailed Description	21
4.3.2	Typedef Documentation	23
4.3.2.1	OpusRepacketizer	23
4.3.3	Function Documentation	23
4.3.3.1	opus_multistream_packet_pad	23
4.3.3.2	opus_multistream_packet_unpad	24
4.3.3.3	opus_packet_pad	24
4.3.3.4	opus_packet_unpad	25
4.3.3.5	opus_repacketizer_cat	25
4.3.3.6	opus_repacketizer_create	26
4.3.3.7	opus_repacketizer_destroy	26
4.3.3.8	opus_repacketizer_get_nb_frames	26
4.3.3.9	opus_repacketizer_get_size	26
4.3.3.10	opus_repacketizer_init	27
4.3.3.11	opus_repacketizer_out	27
4.3.3.12	opus_repacketizer_out_range	28
4.4	Error codes	29
4.4.1	Detailed Description	29
4.4.2	Macro Definition Documentation	29
4.4.2.1	OPUS_ALLOC_FAIL	29
4.4.2.2	OPUS_BAD_ARG	29
4.4.2.3	OPUS_BUFFER_TOO_SMALL	29
4.4.2.4	OPUS_INTERNAL_ERROR	29
4.4.2.5	OPUS_INVALID_PACKET	29

4.4.2.6	OPUS_INVALID_STATE	30
4.4.2.7	OPUS_OK	30
4.4.2.8	OPUS_UNIMPLEMENTED	30
4.5	Pre-defined values for CTL interface	31
4.5.1	Detailed Description	32
4.5.2	Macro Definition Documentation	32
4.5.2.1	OPUS_APPLICATION_AUDIO	32
4.5.2.2	OPUS_APPLICATION_RESTRICTED_LOWDELAY	32
4.5.2.3	OPUS_APPLICATION_VOIP	32
4.5.2.4	OPUS_AUTO	32
4.5.2.5	OPUS_BANDWIDTH_FULLBAND	32
4.5.2.6	OPUS_BANDWIDTH_MEDIUMBAND	32
4.5.2.7	OPUS_BANDWIDTH_NARROWBAND	32
4.5.2.8	OPUS_BANDWIDTH_SUPERWIDEBAND	32
4.5.2.9	OPUS_BANDWIDTH_WIDEBAND	32
4.5.2.10	OPUS_BITRATE_MAX	33
4.5.2.11	OPUS_FRAME_SIZE_100_MS	33
4.5.2.12	OPUS_FRAME_SIZE_10_MS	33
4.5.2.13	OPUS_FRAME_SIZE_120_MS	33
4.5.2.14	OPUS_FRAME_SIZE_20_MS	33
4.5.2.15	OPUS_FRAME_SIZE_2_5_MS	33
4.5.2.16	OPUS_FRAME_SIZE_40_MS	33
4.5.2.17	OPUS_FRAME_SIZE_5_MS	33
4.5.2.18	OPUS_FRAME_SIZE_60_MS	33
4.5.2.19	OPUS_FRAME_SIZE_80_MS	33
4.5.2.20	OPUS_FRAME_SIZE_ARG	33
4.5.2.21	OPUS_SIGNAL_MUSIC	34
4.5.2.22	OPUS_SIGNAL_VOICE	34
4.6	Encoder related CTLs	35
4.6.1	Detailed Description	36
4.6.2	Macro Definition Documentation	36
4.6.2.1	OPUS_GET_APPLICATION	36
4.6.2.2	OPUS_GET_BITRATE	37
4.6.2.3	OPUS_GET_COMPLEXITY	37
4.6.2.4	OPUS_GET_DTX	37
4.6.2.5	OPUS_GET_EXPERT_FRAME_DURATION	38
4.6.2.6	OPUS_GET_FORCE_CHANNELS	38

4.6.2.7	OPUS_GET_INBAND_FEC	38
4.6.2.8	OPUS_GET_LOOKAHEAD	39
4.6.2.9	OPUS_GET_LSB_DEPTH	39
4.6.2.10	OPUS_GET_MAX_BANDWIDTH	39
4.6.2.11	OPUS_GET_PACKET_LOSS_PERC	40
4.6.2.12	OPUS_GET_PREDICTION_DISABLED	40
4.6.2.13	OPUS_GET_SIGNAL	40
4.6.2.14	OPUS_GET_VBR	41
4.6.2.15	OPUS_GET_VBR_CONSTRAINT	41
4.6.2.16	OPUS_SET_APPLICATION	41
4.6.2.17	OPUS_SET_BANDWIDTH	42
4.6.2.18	OPUS_SET_BITRATE	42
4.6.2.19	OPUS_SET_COMPLEXITY	43
4.6.2.20	OPUS_SET_DTX	43
4.6.2.21	OPUS_SET_EXPERT_FRAME_DURATION	43
4.6.2.22	OPUS_SET_FORCE_CHANNELS	44
4.6.2.23	OPUS_SET_INBAND_FEC	44
4.6.2.24	OPUS_SET_LSB_DEPTH	45
4.6.2.25	OPUS_SET_MAX_BANDWIDTH	45
4.6.2.26	OPUS_SET_PACKET_LOSS_PERC	46
4.6.2.27	OPUS_SET_PREDICTION_DISABLED	46
4.6.2.28	OPUS_SET_SIGNAL	46
4.6.2.29	OPUS_SET_VBR	47
4.6.2.30	OPUS_SET_VBR_CONSTRAINT	47
4.7	Generic CTLs	48
4.7.1	Detailed Description	48
4.7.2	Macro Definition Documentation	48
4.7.2.1	OPUS_GET_BANDWIDTH	48
4.7.2.2	OPUS_GET_FINAL_RANGE	49
4.7.2.3	OPUS_GET_PHASE_INVERSION_DISABLED	49
4.7.2.4	OPUS_GET_SAMPLE_RATE	49
4.7.2.5	OPUS_RESET_STATE	50
4.7.2.6	OPUS_SET_PHASE_INVERSION_DISABLED	50
4.8	Decoder related CTLs	51
4.8.1	Detailed Description	51
4.8.2	Macro Definition Documentation	51
4.8.2.1	OPUS_GET_GAIN	51

4.8.2.2	OPUS_GET_LAST_PACKET_DURATION	51
4.8.2.3	OPUS_GET_PITCH	51
4.8.2.4	OPUS_SET_GAIN	52
4.9	Opus library information functions	53
4.9.1	Detailed Description	53
4.9.2	Function Documentation	53
4.9.2.1	opus_get_version_string	53
4.9.2.2	opus_strerror	53
4.10	Multistream specific encoder and decoder CTLs	54
4.10.1	Detailed Description	54
4.10.2	Macro Definition Documentation	54
4.10.2.1	OPUS_MULTISTREAM_GET_DECODER_STATE	54
4.10.2.2	OPUS_MULTISTREAM_GET_ENCODER_STATE	54
4.11	Opus Multistream API	56
4.11.1	Detailed Description	57
4.11.2	Typedef Documentation	57
4.11.2.1	OpusMSDecoder	58
4.11.2.2	OpusMSEncoder	58
4.11.3	Function Documentation	58
4.11.3.1	opus_multistream_decode	58
4.11.3.2	opus_multistream_decode_float	59
4.11.3.3	opus_multistream_decoder_create	59
4.11.3.4	opus_multistream_decoder_ctl	60
4.11.3.5	opus_multistream_decoder_destroy	60
4.11.3.6	opus_multistream_decoder_get_size	60
4.11.3.7	opus_multistream_decoder_init	60
4.11.3.8	opus_multistream_encode	61
4.11.3.9	opus_multistream_encode_float	62
4.11.3.10	opus_multistream_encoder_create	62
4.11.3.11	opus_multistream_encoder_ctl	63
4.11.3.12	opus_multistream_encoder_destroy	63
4.11.3.13	opus_multistream_encoder_get_size	63
4.11.3.14	opus_multistream_encoder_init	64
4.11.3.15	opus_multistream_surround_encoder_create	64
4.11.3.16	opus_multistream_surround_encoder_get_size	64
4.11.3.17	opus_multistream_surround_encoder_init	65
4.12	Opus Custom	66

4.12.1	Detailed Description	67
4.12.2	Typedef Documentation	67
4.12.2.1	OpusCustomDecoder	67
4.12.2.2	OpusCustomEncoder	67
4.12.2.3	OpusCustomMode	67
4.12.3	Function Documentation	68
4.12.3.1	opus_custom_decode	68
4.12.3.2	opus_custom_decode_float	68
4.12.3.3	opus_custom_decoder_create	68
4.12.3.4	opus_custom_decoder_ctl	69
4.12.3.5	opus_custom_decoder_destroy	69
4.12.3.6	opus_custom_decoder_get_size	69
4.12.3.7	opus_custom_decoder_init	69
4.12.3.8	opus_custom_encode	70
4.12.3.9	opus_custom_encode_float	70
4.12.3.10	opus_custom_encoder_create	71
4.12.3.11	opus_custom_encoder_ctl	71
4.12.3.12	opus_custom_encoder_destroy	71
4.12.3.13	opus_custom_encoder_get_size	71
4.12.3.14	opus_custom_mode_create	72
4.12.3.15	opus_custom_mode_destroy	72
5	File Documentation	73
5.1	opus.h File Reference	73
5.1.1	Detailed Description	75
5.2	opus_custom.h File Reference	75
5.2.1	Detailed Description	76
5.2.2	Macro Definition Documentation	76
5.2.2.1	OPUS_CUSTOM_EXPORT	76
5.2.2.2	OPUS_CUSTOM_EXPORT_STATIC	76
5.3	opus_defines.h File Reference	76
5.3.1	Detailed Description	80
5.4	opus_multistream.h File Reference	80
5.4.1	Detailed Description	81
5.5	opus_types.h File Reference	81
5.5.1	Detailed Description	82
5.5.2	Macro Definition Documentation	82

5.5.2.1	opus_int	82
5.5.2.2	opus_int64	82
5.5.2.3	opus_int8	82
5.5.2.4	opus_uint	82
5.5.2.5	opus_uint64	82
5.5.2.6	opus_uint8	82
5.5.3	Typedef Documentation	82
5.5.3.1	opus_int16	82
5.5.3.2	opus_int32	82
5.5.3.3	opus_uint16	82
5.5.3.4	opus_uint32	82

Chapter 1

Opus

The Opus codec is designed for interactive speech and audio transmission over the Internet. It is designed by the IETF Codec Working Group and incorporates technology from Skype's SILK codec and Xiph.Org's CELT codec.

The Opus codec is designed to handle a wide range of interactive audio applications, including Voice over IP, videoconferencing, in-game chat, and even remote live music performances. It can scale from low bit-rate narrowband speech to very high quality stereo music. Its main features are:

- Sampling rates from 8 to 48 kHz
- Bit-rates from 6 kb/s to 510 kb/s
- Support for both constant bit-rate (CBR) and variable bit-rate (VBR)
- Audio bandwidth from narrowband to full-band
- Support for speech and music
- Support for mono and stereo
- Support for multichannel (up to 255 channels)
- Frame sizes from 2.5 ms to 60 ms
- Good loss robustness and packet loss concealment (PLC)
- Floating point and fixed-point implementation

Documentation sections:

- [Opus Encoder](#)
- [Opus Decoder](#)
- [Repacketizer](#)
- [Opus Multistream API](#)
- [Opus library information functions](#)
- [Opus Custom](#)

Chapter 2

Module Index

2.1 Modules

Here is a list of all modules:

Opus Encoder	7
Opus Decoder	13
Repacketizer	21
Error codes	29
Pre-defined values for CTL interface	31
Encoder related CTLs	35
Generic CTLs	48
Decoder related CTLs	51
Opus library information functions	53
Multistream specific encoder and decoder CTLs	54
Opus Multistream API	56
Opus Custom	66

Chapter 3

File Index

3.1 File List

Here is a list of all files with brief descriptions:

opus.h	Opus reference implementation API	73
opus_custom.h	Opus-Custom reference implementation API	75
opus_defines.h	Opus reference implementation constants	76
opus_multistream.h	Opus reference implementation multistream API	80
opus_types.h	Opus reference implementation types	81

Chapter 4

Module Documentation

4.1 Opus Encoder

This page describes the process and functions used to encode Opus.

Typedefs

- typedef struct [OpusEncoder](#) [OpusEncoder](#)
Opus encoder state.

Functions

- int [opus_encoder_get_size](#) (int channels)
Gets the size of an `OpusEncoder` structure.
- [OpusEncoder *](#) [opus_encoder_create](#) ([opus_int32](#) Fs, int channels, int application, int *error)
Allocates and initializes an encoder state.
- int [opus_encoder_init](#) ([OpusEncoder](#) *st, [opus_int32](#) Fs, int channels, int application)
Initializes a previously allocated encoder state The memory pointed to by st must be at least the size returned by [opus_encoder_get_size](#)().
- [opus_int32](#) [opus_encode](#) ([OpusEncoder](#) *st, const [opus_int16](#) *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes an Opus frame.
- [opus_int32](#) [opus_encode_float](#) ([OpusEncoder](#) *st, const float *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes an Opus frame from floating point input.
- void [opus_encoder_destroy](#) ([OpusEncoder](#) *st)
Frees an `OpusEncoder` allocated by [opus_encoder_create](#)().
- int [opus_encoder_ctl](#) ([OpusEncoder](#) *st, int request,...)
Perform a CTL function on an Opus encoder.

4.1.1 Detailed Description

This page describes the process and functions used to encode Opus. Since Opus is a stateful codec, the encoding process starts with creating an encoder state. This can be done with:

```
int         error;
OpusEncoder *enc;
enc = opus_encoder_create(Fs, channels, application, &error)
;
```

From this point, `enc` can be used for encoding an audio stream. An encoder state **must not** be used for more than one stream at the same time. Similarly, the encoder state **must not** be re-initialized for each frame.

While `opus_encoder_create()` allocates memory for the state, it's also possible to initialize pre-allocated memory:

```
int         size;
int         error;
OpusEncoder *enc;
size = opus_encoder_get_size(channels);
enc = malloc(size);
error = opus_encoder_init(enc, Fs, channels, application);
```

where `opus_encoder_get_size()` returns the required size for the encoder state. Note that future versions of this code may change the size, so no assumptions should be made about it.

The encoder state is always continuous in memory and only a shallow copy is sufficient to copy it (e.g. `memcpy()`)

It is possible to change some of the encoder's settings using the `opus_encoder_ctl()` interface. All these settings already default to the recommended value, so they should only be changed when necessary. The most common settings one may want to change are:

```
opus_encoder_ctl(enc, OPUS_SET_BITRATE(bitrate)
);
opus_encoder_ctl(enc, OPUS_SET_COMPLEXITY(
complexity));
opus_encoder_ctl(enc, OPUS_SET_SIGNAL(
signal_type));
```

where

- `bitrate` is in bits per second (b/s)
- `complexity` is a value from 1 to 10, where 1 is the lowest complexity and 10 is the highest
- `signal_type` is either `OPUS_AUTO` (default), `OPUS_SIGNAL_VOICE`, or `OPUS_SIGNAL_MUSIC`

See [Encoder related CTLs](#) and [Generic CTLs](#) for a complete list of parameters that can be set or queried. Most parameters can be set or changed at any time during a stream.

To encode a frame, `opus_encode()` or `opus_encode_float()` must be called with exactly one frame (2.5, 5, 10, 20, 40 or 60 ms) of audio data:

```
len = opus_encode(enc, audio_frame, frame_size, packet, max_packet);
```

where

- `audio_frame` is the audio data in `opus_int16` (or float for `opus_encode_float()`)
- `frame_size` is the duration of the frame in samples (per channel)
- `packet` is the byte array to which the compressed data is written
- `max_packet` is the maximum number of bytes that can be written in the packet (4000 bytes is recommended). Do not use `max_packet` to control VBR target bitrate, instead use the `OPUS_SET_BITRATE` CTL.

`opus_encode()` and `opus_encode_float()` return the number of bytes actually written to the packet. The return value **can be negative**, which indicates that an error has occurred. If the return value is 2 bytes or less, then the packet does not need to be transmitted (DTX).

Once the encoder state is no longer needed, it can be destroyed with

```
opus_encoder_destroy(enc);
```

If the encoder was created with `opus_encoder_init()` rather than `opus_encoder_create()`, then no action is required aside from potentially freeing the memory that was manually allocated for it (calling `free(enc)` for the example above)

4.1.2 Typedef Documentation

4.1.2.1 typedef struct OpusEncoder OpusEncoder

Opus encoder state.

This contains the complete state of an Opus encoder. It is position independent and can be freely copied.

See Also

[opus_encoder_create](#), [opus_encoder_init](#)

4.1.3 Function Documentation

4.1.3.1 `opus_int32 opus_encode (OpusEncoder * st, const opus_int16 * pcm, int frame_size, unsigned char * data, opus_int32 max_data_bytes)`

Encodes an Opus frame.

Parameters

in	<i>st</i>	OpusEncoder*: Encoder state
in	<i>pcm</i>	opus_int16*: Input signal (interleaved if 2 channels). length is <code>frame_size*channels*sizeof(opus_int16)</code>
in	<i>frame_size</i>	int: Number of samples per channel in the input signal. This must be an Opus frame size for the encoder's sampling rate. For example, at 48 kHz the permitted values are 120, 240, 480, 960, 1920, and 2880. Passing in a duration of less than 10 ms (480 samples at 48 kHz) will prevent the encoder from using the LPC or hybrid modes.
out	<i>data</i>	unsigned char*: Output payload. This must contain storage for at least <code>max_data_bytes</code> .
in	<i>max_data_bytes</i>	opus_int32: Size of the allocated memory for the output payload. This may be used to impose an upper limit on the instant bitrate, but should not be used as the only bitrate control. Use OPUS_SET_BITRATE to control the bitrate.

Returns

The length of the encoded packet (in bytes) on success or a negative error code (see [Error codes](#)) on failure.

4.1.3.2 opus_int32 opus_encode_float (OpusEncoder * st, const float * pcm, int frame_size, unsigned char * data, opus_int32 max_data_bytes)

Encodes an Opus frame from floating point input.

Parameters

in	<i>st</i>	OpusEncoder*: Encoder state
in	<i>pcm</i>	float*: Input in float format (interleaved if 2 channels), with a normal range of +/- 1.0. Samples with a range beyond +/-1.0 are supported but will be clipped by decoders using the integer API and should only be used if it is known that the far end supports extended dynamic range. length is frame_size*channels*sizeof(float)
in	<i>frame_size</i>	int: Number of samples per channel in the input signal. This must be an Opus frame size for the encoder's sampling rate. For example, at 48 kHz the permitted values are 120, 240, 480, 960, 1920, and 2880. Passing in a duration of less than 10 ms (480 samples at 48 kHz) will prevent the encoder from using the LPC or hybrid modes.
out	<i>data</i>	unsigned char*: Output payload. This must contain storage for at least <i>max_data_bytes</i> .
in	<i>max_data_bytes</i>	opus_int32: Size of the allocated memory for the output payload. This may be used to impose an upper limit on the instant bitrate, but should not be used as the only bitrate control. Use OPUS_SET_BITRATE to control the bitrate.

Returns

The length of the encoded packet (in bytes) on success or a negative error code (see [Error codes](#)) on failure.

4.1.3.3 OpusEncoder* opus_encoder_create (opus_int32 Fs, int channels, int application, int * error)

Allocates and initializes an encoder state.

There are three coding modes:

[OPUS_APPLICATION_VOIP](#) gives best quality at a given bitrate for voice signals. It enhances the input signal by high-pass filtering and emphasizing formants and harmonics. Optionally it includes in-band forward error correction to protect against packet loss. Use this mode for typical VoIP applications. Because of the enhancement, even at high bitrates the output may sound different from the input.

[OPUS_APPLICATION_AUDIO](#) gives best quality at a given bitrate for most non-voice signals like music. Use this mode for music and mixed (music/voice) content, broadcast, and applications requiring less than 15 ms of coding delay.

[OPUS_APPLICATION_RESTRICTED_LOWDELAY](#) configures low-delay mode that disables the speech-optimized mode in exchange for slightly reduced delay. This mode can only be set on a newly initialized or freshly reset encoder because it changes the codec delay.

This is useful when the caller knows that the speech-optimized modes will not be needed (use with caution).

Parameters

in	<i>Fs</i>	opus_int32: Sampling rate of input signal (Hz) This must be one of 8000, 12000, 16000, 24000, or 48000.
----	-----------	---

in	<i>channels</i>	int: Number of channels (1 or 2) in input signal
in	<i>application</i>	int: Coding mode (OPUS_APPLICATION_VOIP / OPUS_APPLICATION_AUDIO / OPUS_APPLICATION_RESTRICTED_LOWDELAY)
out	<i>error</i>	int*: Error codes

Note

Regardless of the sampling rate and number channels selected, the Opus encoder can switch to a lower audio bandwidth or number of channels if the bitrate selected is too low. This also means that it is safe to always use 48 kHz stereo input and let the encoder optimize the encoding.

4.1.3.4 int opus_encoder_ctl (OpusEncoder * st, int request, ...)

Perform a CTL function on an Opus encoder.

Generally the request and subsequent arguments are generated by a convenience macro.

Parameters

<i>st</i>	OpusEncoder*: Encoder state.
<i>request</i>	This and all remaining parameters should be replaced by one of the convenience macros in Generic CTLs or Encoder related CTLs .

See Also

[Generic CTLs](#)
[Encoder related CTLs](#)

4.1.3.5 void opus_encoder_destroy (OpusEncoder * st)

Frees an OpusEncoder allocated by [opus_encoder_create\(\)](#).

Parameters

in	<i>st</i>	OpusEncoder*: State to be freed.
----	-----------	----------------------------------

4.1.3.6 int opus_encoder_get_size (int channels)

Gets the size of an OpusEncoder structure.

Parameters

in	<i>channels</i>	int: Number of channels. This must be 1 or 2.
----	-----------------	---

Returns

The size in bytes.

4.1.3.7 int opus_encoder_init (OpusEncoder * st, opus_int32 Fs, int channels, int application)

Initializes a previously allocated encoder state. The memory pointed to by st must be at least the size returned by [opus_encoder_get_size\(\)](#).

This is intended for applications which use their own allocator instead of malloc.

See Also

[opus_encoder_create\(\)](#), [opus_encoder_get_size\(\)](#) To reset a previously initialized state, use the [OPUS_RESET_STATE](#) CTL.

Parameters

in	<i>st</i>	OpusEncoder*: Encoder state
in	<i>Fs</i>	opus_int32: Sampling rate of input signal (Hz) This must be one of 8000, 12000, 16000, 24000, or 48000.
in	<i>channels</i>	int: Number of channels (1 or 2) in input signal
in	<i>application</i>	int: Coding mode (OPUS_APPLICATION_VOIP/OPUS_APPLICATION_AUDIO/OPUS_APPLICATION_RESTRICTED_LOWDELAY)

Return values

OPUS_OK	Success or Error codes
-------------------------	--

4.2 Opus Decoder

This page describes the process and functions used to decode Opus.

Typedefs

- typedef struct [OpusDecoder](#) [OpusDecoder](#)

Opus decoder state.

Functions

- int [opus_decoder_get_size](#) (int channels)
Gets the size of an `OpusDecoder` structure.
- [OpusDecoder](#) * [opus_decoder_create](#) ([opus_int32](#) Fs, int channels, int *error)
Allocates and initializes a decoder state.
- int [opus_decoder_init](#) ([OpusDecoder](#) *st, [opus_int32](#) Fs, int channels)
Initializes a previously allocated decoder state.
- int [opus_decode](#) ([OpusDecoder](#) *st, const unsigned char *data, [opus_int32](#) len, [opus_int16](#) *pcm, int frame_size, int decode_fec)
Decode an Opus packet.
- int [opus_decode_float](#) ([OpusDecoder](#) *st, const unsigned char *data, [opus_int32](#) len, float *pcm, int frame_size, int decode_fec)
Decode an Opus packet with floating point output.
- int [opus_decoder_ctl](#) ([OpusDecoder](#) *st, int request,...)
Perform a CTL function on an Opus decoder.
- void [opus_decoder_destroy](#) ([OpusDecoder](#) *st)
Frees an `OpusDecoder` allocated by `opus_decoder_create()`.
- int [opus_packet_parse](#) (const unsigned char *data, [opus_int32](#) len, unsigned char *out_toc, const unsigned char *frames[48], [opus_int16](#) size[48], int *payload_offset)
Parse an opus packet into one or more frames.
- int [opus_packet_get_bandwidth](#) (const unsigned char *data)
Gets the bandwidth of an Opus packet.
- int [opus_packet_get_samples_per_frame](#) (const unsigned char *data, [opus_int32](#) Fs)
Gets the number of samples per frame from an Opus packet.
- int [opus_packet_get_nb_channels](#) (const unsigned char *data)
Gets the number of channels from an Opus packet.
- int [opus_packet_get_nb_frames](#) (const unsigned char packet[], [opus_int32](#) len)
Gets the number of frames in an Opus packet.
- int [opus_packet_get_nb_samples](#) (const unsigned char packet[], [opus_int32](#) len, [opus_int32](#) Fs)
Gets the number of samples of an Opus packet.
- int [opus_decoder_get_nb_samples](#) (const [OpusDecoder](#) *dec, const unsigned char packet[], [opus_int32](#) len)
Gets the number of samples of an Opus packet.
- void [opus_pcm_soft_clip](#) (float *pcm, int frame_size, int channels, float *softclip_mem)
Applies soft-clipping to bring a float signal within the [-1,1] range.

4.2.1 Detailed Description

This page describes the process and functions used to decode Opus. The decoding process also starts with creating a decoder state. This can be done with:

```
int          error;
OpusDecoder *dec;
dec = opus_decoder_create(Fs, channels, &error);
```

where

- Fs is the sampling rate and must be 8000, 12000, 16000, 24000, or 48000
- channels is the number of channels (1 or 2)
- error will hold the error code in case of failure (or `OPUS_OK` on success)
- the return value is a newly created decoder state to be used for decoding

While `opus_decoder_create()` allocates memory for the state, it's also possible to initialize pre-allocated memory:

```
int          size;
int          error;
OpusDecoder *dec;
size = opus_decoder_get_size(channels);
dec = malloc(size);
error = opus_decoder_init(dec, Fs, channels);
```

where `opus_decoder_get_size()` returns the required size for the decoder state. Note that future versions of this code may change the size, so no assumptions should be made about it.

The decoder state is always continuous in memory and only a shallow copy is sufficient to copy it (e.g. `memcpy()`)

To decode a frame, `opus_decode()` or `opus_decode_float()` must be called with a packet of compressed audio data:

```
frame_size = opus_decode(dec, packet, len, decoded, max_size, 0);
```

where

- packet is the byte array containing the compressed data
- len is the exact number of bytes contained in the packet
- decoded is the decoded audio data in `opus_int16` (or float for `opus_decode_float()`)
- max_size is the max duration of the frame in samples (per channel) that can fit into the `decoded_frame` array

`opus_decode()` and `opus_decode_float()` return the number of samples (per channel) decoded from the packet. If that value is negative, then an error has occurred. This can occur if the packet is corrupted or if the audio buffer is too small to hold the decoded audio.

Opus is a stateful codec with overlapping blocks and as a result Opus packets are not coded independently of each other. Packets must be passed into the decoder serially and in the correct order for a correct decode. Lost packets can be replaced with loss concealment by calling the decoder with a null pointer and zero length for the missing packet.

A single codec state may only be accessed from a single thread at a time and any required locking must be performed by the caller. Separate streams must be decoded with separate decoder states and can be decoded in parallel unless the library was compiled with `NONTHREADSAFE_PSEUDOSTACK` defined.

4.2.2 Typedef Documentation

4.2.2.1 typedef struct OpusDecoder OpusDecoder

Opus decoder state.

This contains the complete state of an Opus decoder. It is position independent and can be freely copied.

See Also

[opus_decoder_create](#), [opus_decoder_init](#)

4.2.3 Function Documentation

4.2.3.1 `int opus_decode (OpusDecoder * st, const unsigned char * data, opus_int32 len, opus_int16 * pcm, int frame_size, int decode_fec)`

Decode an Opus packet.

Parameters

in	<i>st</i>	OpusDecoder*: Decoder state
in	<i>data</i>	char*: Input payload. Use a NULL pointer to indicate packet loss
in	<i>len</i>	opus_int32: Number of bytes in payload*
out	<i>pcm</i>	opus_int16*: Output signal (interleaved if 2 channels). length is frame_size*channels*sizeof(opus_int16)
in	<i>frame_size</i>	Number of samples per channel of available space in <i>pcm</i> . If this is less than the maximum packet duration (120ms; 5760 for 48kHz), this function will not be capable of decoding some packets. In the case of PLC (<i>data</i> ==NULL) or FEC (<i>decode_fec</i> =1), then <i>frame_size</i> needs to be exactly the duration of audio that is missing, otherwise the decoder will not be in the optimal state to decode the next incoming packet. For the PLC and FEC cases, <i>frame_size</i> must be a multiple of 2.5 ms.
in	<i>decode_fec</i>	int: Flag (0 or 1) to request that any in-band forward error correction data be decoded. If no such data is available, the frame is decoded as if it were lost.

Returns

Number of decoded samples or [Error codes](#)

4.2.3.2 `int opus_decode_float (OpusDecoder * st, const unsigned char * data, opus_int32 len, float * pcm, int frame_size, int decode_fec)`

Decode an Opus packet with floating point output.

Parameters

in	<i>st</i>	OpusDecoder*: Decoder state
in	<i>data</i>	char*: Input payload. Use a NULL pointer to indicate packet loss
in	<i>len</i>	opus_int32: Number of bytes in payload
out	<i>pcm</i>	float*: Output signal (interleaved if 2 channels). length is frame_size*channels*sizeof(float)

in	<i>frame_size</i>	Number of samples per channel of available space in <i>pcm</i> . If this is less than the maximum packet duration (120ms; 5760 for 48kHz), this function will not be capable of decoding some packets. In the case of PLC (<i>data</i> ==NULL) or FEC (<i>decode_fec</i> =1), then <i>frame_size</i> needs to be exactly the duration of audio that is missing, otherwise the decoder will not be in the optimal state to decode the next incoming packet. For the PLC and FEC cases, <i>frame_size</i> must be a multiple of 2.5 ms.
in	<i>decode_fec</i>	int: Flag (0 or 1) to request that any in-band forward error correction data be decoded. If no such data is available the frame is decoded as if it were lost.

Returns

Number of decoded samples or [Error codes](#)

4.2.3.3 OpusDecoder* opus_decoder_create (opus_int32 Fs, int channels, int * error)

Allocates and initializes a decoder state.

Parameters

in	<i>Fs</i>	opus_int32: Sample rate to decode at (Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
in	<i>channels</i>	int: Number of channels (1 or 2) to decode
out	<i>error</i>	int*: OPUS_OK Success or Error codes

Internally Opus stores data at 48000 Hz, so that should be the default value for *Fs*. However, the decoder can efficiently decode to buffers at 8, 12, 16, and 24 kHz so if for some reason the caller cannot use data at the full sample rate, or knows the compressed data doesn't use the full frequency range, it can request decoding at a reduced rate. Likewise, the decoder is capable of filling in either mono or interleaved stereo pcm buffers, at the caller's request.

4.2.3.4 int opus_decoder_ctl (OpusDecoder * st, int request, ...)

Perform a CTL function on an Opus decoder.

Generally the request and subsequent arguments are generated by a convenience macro.

Parameters

<i>st</i>	OpusDecoder*: Decoder state.
<i>request</i>	This and all remaining parameters should be replaced by one of the convenience macros in Generic CTLs or Decoder related CTLs .

See Also

[Generic CTLs](#)
[Decoder related CTLs](#)

4.2.3.5 void opus_decoder_destroy (OpusDecoder * st)

Frees an OpusDecoder allocated by [opus_decoder_create\(\)](#).

Parameters

in	<i>st</i>	OpusDecoder*: State to be freed.
----	-----------	----------------------------------

4.2.3.6 int opus_decoder_get_nb_samples (const OpusDecoder * dec, const unsigned char packet[], opus_int32 len)

Gets the number of samples of an Opus packet.

Parameters

in	<i>dec</i>	OpusDecoder*: Decoder state
in	<i>packet</i>	char*: Opus packet
in	<i>len</i>	opus_int32: Length of packet

Returns

Number of samples

Return values

<i>OPUS_BAD_ARG</i>	Insufficient data was passed to the function
<i>OPUS_INVALID_PACKET</i>	The compressed data passed is corrupted or of an unsupported type

4.2.3.7 int opus_decoder_get_size (int channels)

Gets the size of an OpusDecoder structure.

Parameters

in	<i>channels</i>	int: Number of channels. This must be 1 or 2.
----	-----------------	---

Returns

The size in bytes.

4.2.3.8 int opus_decoder_init (OpusDecoder * st, opus_int32 Fs, int channels)

Initializes a previously allocated decoder state.

The state must be at least the size returned by [opus_decoder_get_size\(\)](#). This is intended for applications which use their own allocator instead of malloc.

See Also

[opus_decoder_create](#), [opus_decoder_get_size](#) To reset a previously initialized state, use the [OPUS_RESET_STATE](#) CTL.

Parameters

in	<i>st</i>	OpusDecoder*: Decoder state.
in	<i>Fs</i>	opus_int32: Sampling rate to decode to (Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
in	<i>channels</i>	int: Number of channels (1 or 2) to decode

Return values

OPUS_OK	Success or Error codes
-------------------------	--

4.2.3.9 int opus_packet_get_bandwidth (const unsigned char * data)

Gets the bandwidth of an Opus packet.

Parameters

in	<i>data</i>	char*: Opus packet
----	-------------	--------------------

Return values

OPUS_BANDWIDTH_NARROWBAND	Narrowband (4kHz bandpass)
OPUS_BANDWIDTH_MEDIUMBAND	Mediumband (6kHz bandpass)
OPUS_BANDWIDTH_WIDEBAND	Wideband (8kHz bandpass)
OPUS_BANDWIDTH_SUPERWIDEBAND	Superwideband (12kHz bandpass)
OPUS_BANDWIDTH_FULLBAND	Fullband (20kHz bandpass)
OPUS_INVALID_PACKET	The compressed data passed is corrupted or of an unsupported type

4.2.3.10 int opus_packet_get_nb_channels (const unsigned char * data)

Gets the number of channels from an Opus packet.

Parameters

in	<i>data</i>	char*: Opus packet
----	-------------	--------------------

Returns

Number of channels

Return values

OPUS_INVALID_PACKET	The compressed data passed is corrupted or of an unsupported type
-------------------------------------	---

4.2.3.11 int opus_packet_get_nb_frames (const unsigned char packet[], opus_int32 len)

Gets the number of frames in an Opus packet.

Parameters

in	<i>packet</i>	char*: Opus packet
in	<i>len</i>	opus_int32: Length of packet

Returns

Number of frames

Return values

<i>OPUS_BAD_ARG</i>	Insufficient data was passed to the function
<i>OPUS_INVALID_PACKET</i>	The compressed data passed is corrupted or of an unsupported type

4.2.3.12 `int opus_packet_get_nb_samples (const unsigned char packet[], opus_int32 len, opus_int32 Fs)`

Gets the number of samples of an Opus packet.

Parameters

in	<i>packet</i>	char*: Opus packet
in	<i>len</i>	opus_int32: Length of packet
in	<i>Fs</i>	opus_int32: Sampling rate in Hz. This must be a multiple of 400, or inaccurate results will be returned.

Returns

Number of samples

Return values

<i>OPUS_BAD_ARG</i>	Insufficient data was passed to the function
<i>OPUS_INVALID_PACKET</i>	The compressed data passed is corrupted or of an unsupported type

4.2.3.13 `int opus_packet_get_samples_per_frame (const unsigned char * data, opus_int32 Fs)`

Gets the number of samples per frame from an Opus packet.

Parameters

in	<i>data</i>	char*: Opus packet. This must contain at least one byte of data.
in	<i>Fs</i>	opus_int32: Sampling rate in Hz. This must be a multiple of 400, or inaccurate results will be returned.

Returns

Number of samples per frame.

4.2.3.14 `int opus_packet_parse (const unsigned char * data, opus_int32 len, unsigned char * out_toc, const unsigned char * frames[48], opus_int16 size[48], int * payload_offset)`

Parse an opus packet into one or more frames.

Opus_decode will perform this operation internally so most applications do not need to use this function. This function does not copy the frames, the returned pointers are pointers into the input packet.

Parameters

in	<i>data</i>	char*: Opus packet to be parsed
in	<i>len</i>	opus_int32: size of data
out	<i>out_toc</i>	char*: TOC pointer
out	<i>frames</i>	char*[48] encapsulated frames
out	<i>size</i>	opus_int16[48] sizes of the encapsulated frames
out	<i>payload_offset</i>	int*: returns the position of the payload within the packet (in bytes)

Returns

number of frames

4.2.3.15 void opus_pcm_soft_clip (float * pcm, int frame_size, int channels, float * softclip_mem)

Applies soft-clipping to bring a float signal within the [-1,1] range.

If the signal is already in that range, nothing is done. If there are values outside of [-1,1], then the signal is clipped as smoothly as possible to both fit in the range and avoid creating excessive distortion in the process.

Parameters

in, out	<i>pcm</i>	float*: Input PCM and modified PCM
in	<i>frame_size</i>	int Number of samples per channel to process
in	<i>channels</i>	int: Number of channels
in, out	<i>softclip_mem</i>	float*: State memory for the soft clipping process (one float per channel, initialized to zero)

4.3 Repackitizer

The repackitizer can be used to merge multiple Opus packets into a single packet or alternatively to split Opus packets that have previously been merged.

Typedefs

- typedef struct [OpusRepackitizer](#) [OpusRepackitizer](#)

Functions

- int [opus_repackitizer_get_size](#) (void)
Gets the size of an `OpusRepackitizer` structure.
- [OpusRepackitizer * opus_repackitizer_init](#) ([OpusRepackitizer *rp](#))
(Re)initializes a previously allocated repackitizer state.
- [OpusRepackitizer * opus_repackitizer_create](#) (void)
Allocates memory and initializes the new repackitizer with [opus_repackitizer_init\(\)](#).
- void [opus_repackitizer_destroy](#) ([OpusRepackitizer *rp](#))
Frees an `OpusRepackitizer` allocated by [opus_repackitizer_create\(\)](#).
- int [opus_repackitizer_cat](#) ([OpusRepackitizer *rp](#), const unsigned char *data, [opus_int32 len](#))
Add a packet to the current repackitizer state.
- [opus_int32 opus_repackitizer_out_range](#) ([OpusRepackitizer *rp](#), int begin, int end, unsigned char *data, [opus_int32 maxlen](#))
Construct a new packet from data previously submitted to the repackitizer state via [opus_repackitizer_cat\(\)](#).
- int [opus_repackitizer_get_nb_frames](#) ([OpusRepackitizer *rp](#))
Return the total number of frames contained in packet data submitted to the repackitizer state so far via [opus_repackitizer_cat\(\)](#) since the last call to [opus_repackitizer_init\(\)](#) or [opus_repackitizer_create\(\)](#).
- [opus_int32 opus_repackitizer_out](#) ([OpusRepackitizer *rp](#), unsigned char *data, [opus_int32 maxlen](#))
Construct a new packet from data previously submitted to the repackitizer state via [opus_repackitizer_cat\(\)](#).
- int [opus_packet_pad](#) (unsigned char *data, [opus_int32 len](#), [opus_int32 new_len](#))
Pads a given Opus packet to a larger size (possibly changing the TOC sequence).
- [opus_int32 opus_packet_unpad](#) (unsigned char *data, [opus_int32 len](#))
Remove all padding from a given Opus packet and rewrite the TOC sequence to minimize space usage.
- int [opus_multistream_packet_pad](#) (unsigned char *data, [opus_int32 len](#), [opus_int32 new_len](#), int nb_streams)
Pads a given Opus multi-stream packet to a larger size (possibly changing the TOC sequence).
- [opus_int32 opus_multistream_packet_unpad](#) (unsigned char *data, [opus_int32 len](#), int nb_streams)
Remove all padding from a given Opus multi-stream packet and rewrite the TOC sequence to minimize space usage.

4.3.1 Detailed Description

The repackitizer can be used to merge multiple Opus packets into a single packet or alternatively to split Opus packets that have previously been merged. Splitting valid Opus packets is always guaranteed to succeed, whereas merging valid packets only succeeds if all frames have the same mode, bandwidth, and frame size, and when the total duration of the merged packet is no more than 120 ms. The 120 ms limit comes from the specification and limits decoder memory requirements at a point where framing overhead becomes negligible.

The repackitizer currently only operates on elementary Opus streams. It will not manipulate multistream packets successfully, except in the degenerate case where they consist of data from a single stream.

The repacketizing process starts with creating a repacketizer state, either by calling `opus_repacketizer_create()` or by allocating the memory yourself, e.g.,

```
OpusRepacketizer *rp;
rp = (OpusRepacketizer*)malloc(opus_repacketizer_get_size
    ());
if (rp != NULL)
    opus_repacketizer_init(rp);
```

Then the application should submit packets with `opus_repacketizer_cat()`, extract new packets with `opus_repacketizer_out()` or `opus_repacketizer_out_range()`, and then reset the state for the next set of input packets via `opus_repacketizer_init()`.

For example, to split a sequence of packets into individual frames:

```
unsigned char *data;
int len;
while (get_next_packet(&data, &len))
{
    unsigned char out[1276];
    opus_int32 out_len;
    int nb_frames;
    int err;
    int i;
    err = opus_repacketizer_cat(rp, data, len);
    if (err != OPUS_OK)
    {
        release_packet(data);
        return err;
    }
    nb_frames = opus_repacketizer_get_nb_frames(rp);
    for (i = 0; i < nb_frames; i++)
    {
        out_len = opus_repacketizer_out_range(rp, i, i+1,
            out, sizeof(out));
        if (out_len < 0)
        {
            release_packet(data);
            return (int)out_len;
        }
        output_next_packet(out, out_len);
    }
    opus_repacketizer_init(rp);
    release_packet(data);
}
```

Alternatively, to combine a sequence of frames into packets that each contain up to `TARGET_DURATION_MS` milliseconds of data:

```
// The maximum number of packets with duration TARGET_DURATION_MS occurs
// when the frame size is 2.5 ms, for a total of (TARGET_DURATION_MS*2/5)
// packets.
unsigned char *data[(TARGET_DURATION_MS*2/5)+1];
opus_int32 len[(TARGET_DURATION_MS*2/5)+1];
int nb_packets;
unsigned char out[1277*(TARGET_DURATION_MS*2/2)];
opus_int32 out_len;
int prev_toc;
nb_packets = 0;
while (get_next_packet(data+nb_packets, len+nb_packets))
{
    int nb_frames;
    int err;
    nb_frames = opus_packet_get_nb_frames(data[
        nb_packets], len[nb_packets]);
    if (nb_frames < 1)
    {
        release_packets(data, nb_packets+1);
        return nb_frames;
    }
    nb_frames += opus_repacketizer_get_nb_frames(
        rp);
```



```

// If adding the next packet would exceed our target, or it has an
// incompatible TOC sequence, output the packets we already have before
// submitting it.
// N.B., The nb_packets > 0 check ensures we've submitted at least one
// packet since the last call to opus_repackitizer_init(). Otherwise a
// single packet longer than TARGET_DURATION_MS would cause us to try to
// output an (invalid) empty packet. It also ensures that prev_toc has
// been set to a valid value. Additionally, len[nb_packets] > 0 is
// guaranteed by the call to opus_packet_get_nb_frames() above, so the
// reference to data[nb_packets][0] should be valid.
if (nb_packets > 0 && (
    (prev_toc & 0xFC) != (data[nb_packets][0] & 0xFC)) ||
    opus_packet_get_samples_per_frame(data[
        nb_packets], 48000)*nb_frames >
    TARGET_DURATION_MS*48))
{
    out_len = opus_repackitizer_out(rp, out, sizeof(out));
    if (out_len < 0)
    {
        release_packets(data, nb_packets+1);
        return (int)out_len;
    }
    output_next_packet(out, out_len);
    opus_repackitizer_init(rp);
    release_packets(data, nb_packets);
    data[0] = data[nb_packets];
    len[0] = len[nb_packets];
    nb_packets = 0;
}
err = opus_repackitizer_cat(rp, data[nb_packets], len[
    nb_packets]);
if (err != OPUS_OK)
{
    release_packets(data, nb_packets+1);
    return err;
}
prev_toc = data[nb_packets][0];
nb_packets++;
}
// Output the final, partial packet.
if (nb_packets > 0)
{
    out_len = opus_repackitizer_out(rp, out, sizeof(out));
    release_packets(data, nb_packets);
    if (out_len < 0)
        return (int)out_len;
    output_next_packet(out, out_len);
}

```

An alternate way of merging packets is to simply call `opus_repackitizer_cat()` unconditionally until it fails. At that point, the merged packet can be obtained with `opus_repackitizer_out()` and the input packet for which `opus_repackitizer_cat()` needs to be re-added to a newly reinitialized repackitizer state.

4.3.2 Typedef Documentation

4.3.2.1 typedef struct OpusRepackitizer OpusRepackitizer

4.3.3 Function Documentation

4.3.3.1 int opus_multistream_packet_pad (unsigned char * data, opus_int32 len, opus_int32 new_len, int nb_streams)

Pads a given Opus multi-stream packet to a larger size (possibly changing the TOC sequence).

Parameters

in,out	<i>data</i>	const unsigned char*: The buffer containing the packet to pad.
	<i>len</i>	opus_int32: The size of the packet. This must be at least 1.
	<i>new_len</i>	opus_int32: The desired size of the packet after padding. This must be at least 1.

	<i>nb_streams</i>	opus_int32: The number of streams (not channels) in the packet. This must be at least as large as len.
--	-------------------	--

Returns

an error code

Return values

OPUS_OK	on success.
OPUS_BAD_ARG	len was less than 1.
OPUS_INVALID_PACKET	data did not contain a valid Opus packet.

4.3.3.2 opus_int32 opus_multistream_packet_unpad (unsigned char * data, opus_int32 len, int nb_streams)

Remove all padding from a given Opus multi-stream packet and rewrite the TOC sequence to minimize space usage.

Parameters

in, out	<i>data</i>	const unsigned char*: The buffer containing the packet to strip.
	<i>len</i>	opus_int32: The size of the packet. This must be at least 1.
	<i>nb_streams</i>	opus_int32: The number of streams (not channels) in the packet. This must be at least 1.

Returns

The new size of the output packet on success, or an error code on failure.

Return values

OPUS_BAD_ARG	len was less than 1 or new_len was less than len.
OPUS_INVALID_PACKET	data did not contain a valid Opus packet.

4.3.3.3 int opus_packet_pad (unsigned char * data, opus_int32 len, opus_int32 new_len)

Pads a given Opus packet to a larger size (possibly changing the TOC sequence).

Parameters

in, out	<i>data</i>	const unsigned char*: The buffer containing the packet to pad.
	<i>len</i>	opus_int32: The size of the packet. This must be at least 1.
	<i>new_len</i>	opus_int32: The desired size of the packet after padding. This must be at least as large as len.

Returns

an error code

Return values

OPUS_OK	<i>on success.</i>
OPUS_BAD_ARG	<i>len was less than 1 or new_len was less than len.</i>
OPUS_INVALID_PACKET	<i>data did not contain a valid Opus packet.</i>

4.3.3.4 `opus_int32 opus_packet_unpad (unsigned char * data, opus_int32 len)`

Remove all padding from a given Opus packet and rewrite the TOC sequence to minimize space usage.

Parameters

<i>in, out</i>	<i>data</i>	<code>const unsigned char*</code> : The buffer containing the packet to strip.
	<i>len</i>	<code>opus_int32</code> : The size of the packet. This must be at least 1.

Returns

The new size of the output packet on success, or an error code on failure.

Return values

OPUS_BAD_ARG	<i>len was less than 1.</i>
OPUS_INVALID_PACKET	<i>data did not contain a valid Opus packet.</i>

4.3.3.5 `int opus_repacketizer_cat (OpusRepacketizer * rp, const unsigned char * data, opus_int32 len)`

Add a packet to the current repackitizer state.

This packet must match the configuration of any packets already submitted for repackitization since the last call to [opus_repacketizer_init\(\)](#). This means that it must have the same coding mode, audio bandwidth, frame size, and channel count. This can be checked in advance by examining the top 6 bits of the first byte of the packet, and ensuring they match the top 6 bits of the first byte of any previously submitted packet. The total duration of audio in the repackitizer state also must not exceed 120 ms, the maximum duration of a single packet, after adding this packet.

The contents of the current repackitizer state can be extracted into new packets using [opus_repacketizer_out\(\)](#) or [opus_repacketizer_out_range\(\)](#).

In order to add a packet with a different configuration or to add more audio beyond 120 ms, you must clear the repackitizer state by calling [opus_repacketizer_init\(\)](#). If a packet is too large to add to the current repackitizer state, no part of it is added, even if it contains multiple frames, some of which might fit. If you wish to be able to add parts of such packets, you should first use another repackitizer to split the packet into pieces and add them individually.

See Also

[opus_repacketizer_out_range](#)
[opus_repacketizer_out](#)
[opus_repacketizer_init](#)

Parameters

	<i>rp</i>	<code>OpusRepacketizer*</code> : The repackitizer state to which to add the packet.
<i>in</i>	<i>data</i>	<code>const unsigned char*</code> : The packet data. The application must ensure this pointer remains valid until the next call to opus_repacketizer_init() or opus_repacketizer_destroy() .
	<i>len</i>	<code>opus_int32</code> : The number of bytes in the packet data.

Returns

An error code indicating whether or not the operation succeeded.

Return values

OPUS_OK	The packet's contents have been added to the repacketizer state.
OPUS_INVALID_PACKET	The packet did not have a valid TOC sequence, the packet's TOC sequence was not compatible with previously submitted packets (because the coding mode, audio bandwidth, frame size, or channel count did not match), or adding this packet would increase the total amount of audio stored in the repacketizer state to more than 120 ms.

4.3.3.6 OpusRepackitizer* opus_repacketizer_create (void)

Allocates memory and initializes the new repacketizer with [opus_repacketizer_init\(\)](#).

4.3.3.7 void opus_repacketizer_destroy (OpusRepackitizer * rp)

Frees an `OpusRepackitizer` allocated by [opus_repacketizer_create\(\)](#).

Parameters

<code>in</code>	<code>rp</code>	<code>OpusRepackitizer*</code> : State to be freed.
-----------------	-----------------	---

4.3.3.8 int opus_repacketizer_get_nb_frames (OpusRepackitizer * rp)

Return the total number of frames contained in packet data submitted to the repacketizer state so far via [opus_repacketizer_cat\(\)](#) since the last call to [opus_repacketizer_init\(\)](#) or [opus_repacketizer_create\(\)](#).

This defines the valid range of packets that can be extracted with [opus_repacketizer_out_range\(\)](#) or [opus_repacketizer_out\(\)](#).

Parameters

<code>rp</code>	<code>OpusRepackitizer*</code> : The repacketizer state containing the frames.
-----------------	--

Returns

The total number of frames contained in the packet data submitted to the repacketizer state.

4.3.3.9 int opus_repacketizer_get_size (void)

Gets the size of an `OpusRepackitizer` structure.

Returns

The size in bytes.

4.3.3.10 `OpusRepackitizer* opus_repackitizer_init (OpusRepackitizer * rp)`

(Re)initializes a previously allocated repackitizer state.

The state must be at least the size returned by `opus_repackitizer_get_size()`. This can be used for applications which use their own allocator instead of `malloc()`. It must also be called to reset the queue of packets waiting to be repackitized, which is necessary if the maximum packet duration of 120 ms is reached or if you wish to submit packets with a different Opus configuration (coding mode, audio bandwidth, frame size, or channel count). Failure to do so will prevent a new packet from being added with `opus_repackitizer_cat()`.

See Also

[opus_repackitizer_create](#)
[opus_repackitizer_get_size](#)
[opus_repackitizer_cat](#)

Parameters

<i>rp</i>	OpusRepackitizer*: The repackitizer state to (re)initialize.
-----------	--

Returns

A pointer to the same repackitizer state that was passed in.

4.3.3.11 `opus_int32 opus_repackitizer_out (OpusRepackitizer * rp, unsigned char * data, opus_int32 maxlen)`

Construct a new packet from data previously submitted to the repackitizer state via `opus_repackitizer_cat()`.

This is a convenience routine that returns all the data submitted so far in a single packet. It is equivalent to calling

```
opus_repackitizer_out_range(rp, 0,
    opus_repackitizer_get_nb_frames(rp),
    data, maxlen)
```

Parameters

	<i>rp</i>	OpusRepackitizer*: The repackitizer state from which to construct the new packet.
out	<i>data</i>	const unsigned char*: The buffer in which to store the output packet.
	<i>maxlen</i>	opus_int32: The maximum number of bytes to store in the output buffer. In order to guarantee success, this should be at least <code>1277*opus_repackitizer_get_nb_frames(rp)</code> . However, <code>1*opus_repackitizer_get_nb_frames(rp)</code> plus the size of all packet data submitted to the repackitizer since the last call to <code>opus_repackitizer_init()</code> or <code>opus_repackitizer_create()</code> is also sufficient, and possibly much smaller.

Returns

The total size of the output packet on success, or an error code on failure.

Return values

OPUS_BUFFER_TOO_SMALL	<i>maxlen</i> was insufficient to contain the complete output packet.
---------------------------------------	---

4.3.3.12 `opus_int32 opus_repacketizer_out_range (OpusRepacketizer * rp, int begin, int end, unsigned char * data, opus_int32 maxlen)`

Construct a new packet from data previously submitted to the repacketizer state via `opus_repacketizer_cat()`.

Parameters

	<i>rp</i>	OpusRepacketizer*: The repacketizer state from which to construct the new packet.
	<i>begin</i>	int: The index of the first frame in the current repacketizer state to include in the output.
	<i>end</i>	int: One past the index of the last frame in the current repacketizer state to include in the output.
out	<i>data</i>	const unsigned char*: The buffer in which to store the output packet.
	<i>maxlen</i>	opus_int32: The maximum number of bytes to store in the output buffer. In order to guarantee success, this should be at least 1276 for a single frame, or for multiple frames, 1277*(end-begin). However, 1*(end-begin) plus the size of all packet data submitted to the repacketizer since the last call to <code>opus_repacketizer_init()</code> or <code>opus_repacketizer_create()</code> is also sufficient, and possibly much smaller.

Returns

The total size of the output packet on success, or an error code on failure.

Return values

<code>OPUS_BAD_ARG</code>	<code>[begin, end)</code> was an invalid range of frames (<code>begin < 0</code> , <code>begin >= end</code> , or <code>end > opus_repacketizer_get_nb_frames()</code>).
<code>OPUS_BUFFER_TOO_SMALL</code>	<code>maxlen</code> was insufficient to contain the complete output packet.

4.4 Error codes

Macros

- `#define OPUS_OK`
No error.
- `#define OPUS_BAD_ARG`
One or more invalid/out of range arguments.
- `#define OPUS_BUFFER_TOO_SMALL`
Not enough bytes allocated in the buffer.
- `#define OPUS_INTERNAL_ERROR`
An internal error was detected.
- `#define OPUS_INVALID_PACKET`
The compressed data passed is corrupted.
- `#define OPUS_UNIMPLEMENTED`
Invalid/unsupported request number.
- `#define OPUS_INVALID_STATE`
An encoder or decoder structure is invalid or already freed.
- `#define OPUS_ALLOC_FAIL`
Memory allocation has failed.

4.4.1 Detailed Description

4.4.2 Macro Definition Documentation

4.4.2.1 `#define OPUS_ALLOC_FAIL`

Memory allocation has failed.

4.4.2.2 `#define OPUS_BAD_ARG`

One or more invalid/out of range arguments.

4.4.2.3 `#define OPUS_BUFFER_TOO_SMALL`

Not enough bytes allocated in the buffer.

4.4.2.4 `#define OPUS_INTERNAL_ERROR`

An internal error was detected.

4.4.2.5 `#define OPUS_INVALID_PACKET`

The compressed data passed is corrupted.

4.4.2.6 #define OPUS_INVALID_STATE

An encoder or decoder structure is invalid or already freed.

4.4.2.7 #define OPUS_OK

No error.

4.4.2.8 #define OPUS_UNIMPLEMENTED

Invalid/unsupported request number.

4.5 Pre-defined values for CTL interface

Macros

- #define `OPUS_AUTO`
Auto/default setting.
- #define `OPUS_BITRATE_MAX`
Maximum bitrate.
- #define `OPUS_APPLICATION_VOIP`
Best for most VoIP/videoconference applications where listening quality and intelligibility matter most.
- #define `OPUS_APPLICATION_AUDIO`
Best for broadcast/high-fidelity application where the decoded audio should be as close as possible to the input.
- #define `OPUS_APPLICATION_RESTRICTED_LOWDELAY`
Only use when lowest-achievable latency is what matters most.
- #define `OPUS_SIGNAL_VOICE` 3001
Signal being encoded is voice.
- #define `OPUS_SIGNAL_MUSIC` 3002
Signal being encoded is music.
- #define `OPUS_BANDWIDTH_NARROWBAND`
4 kHz bandpass
- #define `OPUS_BANDWIDTH_MEDIUMBAND`
6 kHz bandpass
- #define `OPUS_BANDWIDTH_WIDEBAND`
8 kHz bandpass
- #define `OPUS_BANDWIDTH_SUPERWIDEBAND`
12 kHz bandpass
- #define `OPUS_BANDWIDTH_FULLBAND`
20 kHz bandpass
- #define `OPUS_FRAME_SIZE_ARG` 5000
Select frame size from the argument (default)
- #define `OPUS_FRAME_SIZE_2_5_MS` 5001
Use 2.5 ms frames.
- #define `OPUS_FRAME_SIZE_5_MS` 5002
Use 5 ms frames.
- #define `OPUS_FRAME_SIZE_10_MS` 5003
Use 10 ms frames.
- #define `OPUS_FRAME_SIZE_20_MS` 5004
Use 20 ms frames.
- #define `OPUS_FRAME_SIZE_40_MS` 5005
Use 40 ms frames.
- #define `OPUS_FRAME_SIZE_60_MS` 5006
Use 60 ms frames.
- #define `OPUS_FRAME_SIZE_80_MS` 5007
Use 80 ms frames.
- #define `OPUS_FRAME_SIZE_100_MS` 5008
Use 100 ms frames.
- #define `OPUS_FRAME_SIZE_120_MS` 5009
Use 120 ms frames.

4.5.1 Detailed Description

See Also

[Generic CTLs](#), [Encoder related CTLs](#)

4.5.2 Macro Definition Documentation

4.5.2.1 `#define OPUS_APPLICATION_AUDIO`

Best for broadcast/high-fidelity application where the decoded audio should be as close as possible to the input.

4.5.2.2 `#define OPUS_APPLICATION_RESTRICTED_LOWDELAY`

Only use when lowest-achievable latency is what matters most.

Voice-optimized modes cannot be used.

4.5.2.3 `#define OPUS_APPLICATION_VOIP`

Best for most VoIP/videoconference applications where listening quality and intelligibility matter most.

4.5.2.4 `#define OPUS_AUTO`

Auto/default setting.

4.5.2.5 `#define OPUS_BANDWIDTH_FULLBAND`

20 kHz bandpass

4.5.2.6 `#define OPUS_BANDWIDTH_MEDIUMBAND`

6 kHz bandpass

4.5.2.7 `#define OPUS_BANDWIDTH_NARROWBAND`

4 kHz bandpass

4.5.2.8 `#define OPUS_BANDWIDTH_SUPERWIDEBAND`

12 kHz bandpass

4.5.2.9 `#define OPUS_BANDWIDTH_WIDEBAND`

8 kHz bandpass

4.5.2.10 `#define OPUS_BITRATE_MAX`

Maximum bitrate.

4.5.2.11 `#define OPUS_FRAMESIZE_100_MS 5008`

Use 100 ms frames.

4.5.2.12 `#define OPUS_FRAMESIZE_10_MS 5003`

Use 10 ms frames.

4.5.2.13 `#define OPUS_FRAMESIZE_120_MS 5009`

Use 120 ms frames.

4.5.2.14 `#define OPUS_FRAMESIZE_20_MS 5004`

Use 20 ms frames.

4.5.2.15 `#define OPUS_FRAMESIZE_2_5_MS 5001`

Use 2.5 ms frames.

4.5.2.16 `#define OPUS_FRAMESIZE_40_MS 5005`

Use 40 ms frames.

4.5.2.17 `#define OPUS_FRAMESIZE_5_MS 5002`

Use 5 ms frames.

4.5.2.18 `#define OPUS_FRAMESIZE_60_MS 5006`

Use 60 ms frames.

4.5.2.19 `#define OPUS_FRAMESIZE_80_MS 5007`

Use 80 ms frames.

4.5.2.20 `#define OPUS_FRAMESIZE_ARG 5000`

Select frame size from the argument (default)

4.5.2.21 `#define OPUS_SIGNAL_MUSIC 3002`

Signal being encoded is music.

4.5.2.22 `#define OPUS_SIGNAL_VOICE 3001`

Signal being encoded is voice.

4.6 Encoder related CTLs

These are convenience macros for use with the `opus_encode_ctl` interface.

Macros

- `#define OPUS_SET_COMPLEXITY(x)`
Configures the encoder's computational complexity.
- `#define OPUS_GET_COMPLEXITY(x)`
Gets the encoder's complexity configuration.
- `#define OPUS_SET_BITRATE(x)`
Configures the bitrate in the encoder.
- `#define OPUS_GET_BITRATE(x)`
Gets the encoder's bitrate configuration.
- `#define OPUS_SET_VBR(x)`
Enables or disables variable bitrate (VBR) in the encoder.
- `#define OPUS_GET_VBR(x)`
Determine if variable bitrate (VBR) is enabled in the encoder.
- `#define OPUS_SET_VBR_CONSTRAINT(x)`
Enables or disables constrained VBR in the encoder.
- `#define OPUS_GET_VBR_CONSTRAINT(x)`
Determine if constrained VBR is enabled in the encoder.
- `#define OPUS_SET_FORCE_CHANNELS(x)`
Configures mono/stereo forcing in the encoder.
- `#define OPUS_GET_FORCE_CHANNELS(x)`
Gets the encoder's forced channel configuration.
- `#define OPUS_SET_MAX_BANDWIDTH(x)`
Configures the maximum bandpass that the encoder will select automatically.
- `#define OPUS_GET_MAX_BANDWIDTH(x)`
Gets the encoder's configured maximum allowed bandpass.
- `#define OPUS_SET_BANDWIDTH(x)`
Sets the encoder's bandpass to a specific value.
- `#define OPUS_SET_SIGNAL(x)`
Configures the type of signal being encoded.
- `#define OPUS_GET_SIGNAL(x)`
Gets the encoder's configured signal type.
- `#define OPUS_SET_APPLICATION(x)`
Configures the encoder's intended application.
- `#define OPUS_GET_APPLICATION(x)`
Gets the encoder's configured application.
- `#define OPUS_GET_LOOKAHEAD(x)`
Gets the total samples of delay added by the entire codec.
- `#define OPUS_SET_INBAND_FEC(x)`
Configures the encoder's use of inband forward error correction (FEC).
- `#define OPUS_GET_INBAND_FEC(x)`
Gets encoder's configured use of inband forward error correction.
- `#define OPUS_SET_PACKET_LOSS_PERC(x)`

- Configures the encoder's expected packet loss percentage.*

 - #define [OPUS_GET_PACKET_LOSS_PERC\(x\)](#)

Gets the encoder's configured packet loss percentage.
- #define [OPUS_SET_DTX\(x\)](#)

Configures the encoder's use of discontinuous transmission (DTX).
- #define [OPUS_GET_DTX\(x\)](#)

Gets encoder's configured use of discontinuous transmission.
- #define [OPUS_SET_LSB_DEPTH\(x\)](#)

Configures the depth of signal being encoded.
- #define [OPUS_GET_LSB_DEPTH\(x\)](#)

Gets the encoder's configured signal depth.
- #define [OPUS_SET_EXPERT_FRAME_DURATION\(x\)](#)

Configures the encoder's use of variable duration frames.
- #define [OPUS_GET_EXPERT_FRAME_DURATION\(x\)](#)

Gets the encoder's configured use of variable duration frames.
- #define [OPUS_SET_PREDICTION_DISABLED\(x\)](#)

If set to 1, disables almost all use of prediction, making frames almost completely independent.
- #define [OPUS_GET_PREDICTION_DISABLED\(x\)](#)

Gets the encoder's configured prediction status.

4.6.1 Detailed Description

These are convenience macros for use with the `opus_encode_ctl` interface. They are used to generate the appropriate series of arguments for that call, passing the correct type, size and so on as expected for each particular request.

Some usage examples:

```
int ret;
ret = opus_encoder_ctl(enc_ctx, OPUS_SET_BANDWIDTH
    (OPUS_AUTO));
if (ret != OPUS_OK) return ret;

opus_int32 rate;
opus_encoder_ctl(enc_ctx, OPUS_GET_BANDWIDTH(
    &rate));

opus_encoder_ctl(enc_ctx, OPUS_RESET_STATE);
```

See Also

[Generic CTLs, Opus Encoder](#)

4.6.2 Macro Definition Documentation

4.6.2.1 #define OPUS_GET_APPLICATION(x)

Gets the encoder's configured application.

See Also

[OPUS_SET_APPLICATION](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: OPUS_APPLICATION_VOIP Process signal for improved speech intelligibility. OPUS_APPLICATION_AUDIO Favor faithfulness to the original input. OPUS_APPLICATION_RESTRICTED_LOWDELAY Configure the minimum possible coding delay by disabling certain modes of operation.
-----	---	--

4.6.2.2 #define OPUS_GET_BITRATE(x)

Gets the encoder's bitrate configuration.

See Also

[OPUS_SET_BITRATE](#)

Parameters

out	x	opus_int32 *: Returns the bitrate in bits per second. The default is determined based on the number of channels and the input sampling rate.
-----	---	--

4.6.2.3 #define OPUS_GET_COMPLEXITY(x)

Gets the encoder's complexity configuration.

See Also

[OPUS_SET_COMPLEXITY](#)

Parameters

out	x	opus_int32 *: Returns a value in the range 0-10, inclusive.
-----	---	---

4.6.2.4 #define OPUS_GET_DTX(x)

Gets encoder's configured use of discontinuous transmission.

See Also

[OPUS_SET_DTX](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 DTX disabled (default). 1 DTX enabled.
-----	---	---

4.6.2.5 #define OPUS_GET_EXPERT_FRAME_DURATION(x)

Gets the encoder's configured use of variable duration frames.

See Also

[OPUS_SET_EXPERT_FRAME_DURATION](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: OPUS_FRAME_SIZE_ARG Select frame size from the argument (default). OPUS_FRAME_SIZE_2_5_MS Use 2.5 ms frames. OPUS_FRAME_SIZE_5_MS Use 5 ms frames. OPUS_FRAME_SIZE_10_MS Use 10 ms frames. OPUS_FRAME_SIZE_20_MS Use 20 ms frames. OPUS_FRAME_SIZE_40_MS Use 40 ms frames. OPUS_FRAME_SIZE_60_MS Use 60 ms frames. OPUS_FRAME_SIZE_80_MS Use 80 ms frames. OPUS_FRAME_SIZE_100_MS Use 100 ms frames. OPUS_FRAME_SIZE_120_MS Use 120 ms frames.
-----	---	---

4.6.2.6 #define OPUS_GET_FORCE_CHANNELS(x)

Gets the encoder's forced channel configuration.

See Also

[OPUS_SET_FORCE_CHANNELS](#)

Parameters

out	x	opus_int32 *: OPUS_AUTO Not forced (default) 1 Forced mono 2 Forced stereo
-----	---	--

4.6.2.7 #define OPUS_GET_INBAND_FEC(x)

Gets encoder's configured use of inband forward error correction.

See Also

[OPUS_SET_INBAND_FEC](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 Inband FEC disabled (default). 1 Inband FEC enabled.
-----	---	---

4.6.2.8 #define OPUS_GET_LOOKAHEAD(x)

Gets the total samples of delay added by the entire codec.

This can be queried by the encoder and then the provided number of samples can be skipped on from the start of the decoder's output to provide time aligned input and output. From the perspective of a decoding application the real data begins this many samples late.

The decoder contribution to this delay is identical for all decoders, but the encoder portion of the delay may vary from implementation to implementation, version to version, or even depend on the encoder's initial configuration. Applications needing delay compensation should call this CTL rather than hard-coding a value.

Parameters

out	x	opus_int32 *: Number of lookahead samples
-----	---	---

4.6.2.9 #define OPUS_GET_LSB_DEPTH(x)

Gets the encoder's configured signal depth.

See Also

[OPUS_SET_LSB_DEPTH](#)

Parameters

out	x	opus_int32 *: Input precision in bits, between 8 and 24 (default: 24).
-----	---	--

4.6.2.10 #define OPUS_GET_MAX_BANDWIDTH(x)

Gets the encoder's configured maximum allowed bandpass.

See Also

[OPUS_SET_MAX_BANDWIDTH](#)

Parameters

out	x	opus_int32 *: Allowed values: OPUS_BANDWIDTH_NARROWBAND 4 kHz passband OPUS_BANDWIDTH_MEDIUMBAND 6 kHz passband OPUS_BANDWIDTH_WIDEBAND 8 kHz passband OPUS_BANDWIDTH_SUPERWIDEBAND 12 kHz passband OPUS_BANDWIDTH_FULLBAND 20 kHz passband (default)
-----	---	--

4.6.2.11 #define OPUS_GET_PACKET_LOSS_PERC(x)

Gets the encoder's configured packet loss percentage.

See Also

[OPUS_SET_PACKET_LOSS_PERC](#)

Parameters

out	x	opus_int32 *: Returns the configured loss percentage in the range 0-100, inclusive (default: 0).
-----	---	--

4.6.2.12 #define OPUS_GET_PREDICTION_DISABLED(x)

Gets the encoder's configured prediction status.

See Also

[OPUS_SET_PREDICTION_DISABLED](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 Prediction enabled (default). 1 Prediction disabled.
-----	---	---

4.6.2.13 #define OPUS_GET_SIGNAL(x)

Gets the encoder's configured signal type.

See Also

[OPUS_SET_SIGNAL](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: OPUS_AUTO (default) OPUS_SIGNAL_VOICE Bias thresholds towards choosing LPC or Hybrid modes. OPUS_SIGNAL_MUSIC Bias thresholds towards choosing MDCT modes.
-----	---	--

4.6.2.14 #define OPUS_GET_VBR(x)

Determine if variable bitrate (VBR) is enabled in the encoder.

See Also

[OPUS_SET_VBR](#)
[OPUS_GET_VBR_CONSTRAINT](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 Hard CBR. 1 VBR (default). The exact type of VBR may be retrieved via OPUS_GET_VBR- _CONSTRAINT .
-----	---	--

4.6.2.15 #define OPUS_GET_VBR_CONSTRAINT(x)

Determine if constrained VBR is enabled in the encoder.

See Also

[OPUS_SET_VBR_CONSTRAINT](#)
[OPUS_GET_VBR](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 Unconstrained VBR. 1 Constrained VBR (default).
-----	---	--

4.6.2.16 #define OPUS_SET_APPLICATION(x)

Configures the encoder's intended application.

The initial value is a mandatory argument to the encoder_create function.

See Also

[OPUS_GET_APPLICATION](#)

Parameters

in	x	opus_int32: Returns one of the following values: OPUS_APPLICATION_VOIP Process signal for improved speech intelligibility. OPUS_APPLICATION_AUDIO Favor faithfulness to the original input. OPUS_APPLICATION_RESTRICTED_LOWDELAY Configure the minimum possible coding delay by disabling certain modes of operation.
----	---	--

4.6.2.17 #define OPUS_SET_BANDWIDTH(x)

Sets the encoder's bandpass to a specific value.

This prevents the encoder from automatically selecting the bandpass based on the available bitrate. If an application knows the bandpass of the input audio it is providing, it should normally use [OPUS_SET_MAX_BANDWIDTH](#) instead, which still gives the encoder the freedom to reduce the bandpass when the bitrate becomes too low, for better overall quality.

See Also

[OPUS_GET_BANDWIDTH](#)

Parameters

in	x	opus_int32: Allowed values: OPUS_AUTO (default) OPUS_BANDWIDTH_NARROWBAND 4 kHz passband OPUS_BANDWIDTH_MEDIUMBAND 6 kHz passband OPUS_BANDWIDTH_WIDEBAND 8 kHz passband OPUS_BANDWIDTH_SUPERWIDEBAND 12 kHz passband OPUS_BANDWIDTH_FULLBAND 20 kHz passband
----	---	---

4.6.2.18 #define OPUS_SET_BITRATE(x)

Configures the bitrate in the encoder.

Rates from 500 to 512000 bits per second are meaningful, as well as the special values [OPUS_AUTO](#) and [OPUS_BITRATE_MAX](#). The value [OPUS_BITRATE_MAX](#) can be used to cause the codec to use as much rate as it can, which is useful for controlling the rate by adjusting the output buffer size.

See Also

[OPUS_GET_BITRATE](#)

Parameters

in	x	opus_int32: Bitrate in bits per second. The default is determined based on the number of channels and the input sampling rate.
----	---	--

4.6.2.19 #define OPUS_SET_COMPLEXITY(x)

Configures the encoder's computational complexity.

The supported range is 0-10 inclusive with 10 representing the highest complexity.

See Also

[OPUS_GET_COMPLEXITY](#)

Parameters

in	x	opus_int32: Allowed values: 0-10, inclusive.
----	---	--

4.6.2.20 #define OPUS_SET_DTX(x)

Configures the encoder's use of discontinuous transmission (DTX).

Note

This is only applicable to the LPC layer

See Also

[OPUS_GET_DTX](#)

Parameters

in	x	opus_int32: Allowed values: 0 Disable DTX (default). 1 Enabled DTX.
----	---	---

4.6.2.21 #define OPUS_SET_EXPERT_FRAME_DURATION(x)

Configures the encoder's use of variable duration frames.

When variable duration is enabled, the encoder is free to use a shorter frame size than the one requested in the opus_encode*() call. It is then the user's responsibility to verify how much audio was encoded by checking the ToC byte of the encoded packet. The part of the audio that was not encoded needs to be resent to the encoder for the next call. Do not use this option unless you **really** know what you are doing.

See Also

[OPUS_GET_EXPERT_FRAME_DURATION](#)

Parameters

in	x	opus_int32: Allowed values: OPUS_FRAME_SIZE_ARG Select frame size from the argument (default). OPUS_FRAME_SIZE_2_5_MS Use 2.5 ms frames. OPUS_FRAME_SIZE_5_MS Use 5 ms frames. OPUS_FRAME_SIZE_10_MS Use 10 ms frames. OPUS_FRAME_SIZE_20_MS Use 20 ms frames. OPUS_FRAME_SIZE_40_MS Use 40 ms frames. OPUS_FRAME_SIZE_60_MS Use 60 ms frames. OPUS_FRAME_SIZE_80_MS Use 80 ms frames. OPUS_FRAME_SIZE_100_MS Use 100 ms frames. OPUS_FRAME_SIZE_120_MS Use 120 ms frames.
----	---	--

4.6.2.22 #define OPUS_SET_FORCE_CHANNELS(x)

Configures mono/stereo forcing in the encoder.

This can force the encoder to produce packets encoded as either mono or stereo, regardless of the format of the input audio. This is useful when the caller knows that the input signal is currently a mono source embedded in a stereo stream.

See Also

[OPUS_GET_FORCE_CHANNELS](#)

Parameters

in	x	opus_int32: Allowed values: OPUS_AUTO Not forced (default) 1 Forced mono 2 Forced stereo
----	---	--

4.6.2.23 #define OPUS_SET_INBAND_FEC(x)

Configures the encoder's use of inband forward error correction (FEC).

Note

This is only applicable to the LPC layer

See Also

[OPUS_GET_INBAND_FEC](#)

Parameters

in	x	opus_int32: Allowed values: 0 Disable inband FEC (default). 1 Enable inband FEC.
----	---	--

4.6.2.24 #define OPUS_SET_LSB_DEPTH(x)

Configures the depth of signal being encoded.

This is a hint which helps the encoder identify silence and near-silence. It represents the number of significant bits of linear intensity below which the signal contains ignorable quantization or other noise.

For example, [OPUS_SET_LSB_DEPTH\(14\)](#) would be an appropriate setting for G.711 u-law input. [OPUS_SET_LSB_DEPTH\(16\)](#) would be appropriate for 16-bit linear pcm input with [opus_encode_float\(\)](#).

When using [opus_encode\(\)](#) instead of [opus_encode_float\(\)](#), or when libopus is compiled for fixed-point, the encoder uses the minimum of the value set here and the value 16.

See Also

[OPUS_GET_LSB_DEPTH](#)

Parameters

in	x	opus_int32: Input precision in bits, between 8 and 24 (default: 24).
----	---	--

4.6.2.25 #define OPUS_SET_MAX_BANDWIDTH(x)

Configures the maximum bandpass that the encoder will select automatically.

Applications should normally use this instead of [OPUS_SET_BANDWIDTH](#) (leaving that set to the default, [OPUS_AUTO](#)). This allows the application to set an upper bound based on the type of input it is providing, but still gives the encoder the freedom to reduce the bandpass when the bitrate becomes too low, for better overall quality.

See Also

[OPUS_GET_MAX_BANDWIDTH](#)

Parameters

in	x	opus_int32: Allowed values: OPUS_BANDWIDTH_NARROWBAND 4 kHz passband OPUS_BANDWIDTH_MEDIUMBAND 6 kHz passband OPUS_BANDWIDTH_WIDEBAND 8 kHz passband OPUS_BANDWIDTH_SUPERWIDEBAND 12 kHz passband OPUS_BANDWIDTH_FULLBAND 20 kHz passband (default)
----	---	---

4.6.2.26 #define OPUS_SET_PACKET_LOSS_PERC(x)

Configures the encoder's expected packet loss percentage.

Higher values trigger progressively more loss resistant behavior in the encoder at the expense of quality at a given bitrate in the absence of packet loss, but greater quality under loss.

See Also

[OPUS_GET_PACKET_LOSS_PERC](#)

Parameters

in	x	opus_int32: Loss percentage in the range 0-100, inclusive (default: 0).
----	---	---

4.6.2.27 #define OPUS_SET_PREDICTION_DISABLED(x)

If set to 1, disables almost all use of prediction, making frames almost completely independent.

This reduces quality.

See Also

[OPUS_GET_PREDICTION_DISABLED](#)

Parameters

in	x	opus_int32: Allowed values: 0 Enable prediction (default). 1 Disable prediction.
----	---	--

4.6.2.28 #define OPUS_SET_SIGNAL(x)

Configures the type of signal being encoded.

This is a hint which helps the encoder's mode selection.

See Also

[OPUS_GET_SIGNAL](#)

Parameters

in	x	opus_int32: Allowed values: OPUS_AUTO (default) OPUS_SIGNAL_VOICE Bias thresholds towards choosing LPC or Hybrid modes. OPUS_SIGNAL_MUSIC Bias thresholds towards choosing MDCT modes.
----	---	---

4.6.2.29 `#define OPUS_SET_VBR(x)`

Enables or disables variable bitrate (VBR) in the encoder.

The configured bitrate may not be met exactly because frames must be an integer number of bytes in length.

See Also

[OPUS_GET_VBR](#)
[OPUS_SET_VBR_CONSTRAINT](#)

Parameters

in	x	opus_int32: Allowed values: 0 Hard CBR. For LPC/hybrid modes at very low bit-rate, this can cause noticeable quality degradation. 1 VBR (default). The exact type of VBR is controlled by OPUS_SET_VBR_CONSTRAINT .
----	---	---

4.6.2.30 `#define OPUS_SET_VBR_CONSTRAINT(x)`

Enables or disables constrained VBR in the encoder.

This setting is ignored when the encoder is in CBR mode.

Warning

Only the MDCT mode of Opus currently heeds the constraint. Speech mode ignores it completely, hybrid mode may fail to obey it if the LPC layer uses more bitrate than the constraint would have permitted.

See Also

[OPUS_GET_VBR_CONSTRAINT](#)
[OPUS_SET_VBR](#)

Parameters

in	x	opus_int32: Allowed values: 0 Unconstrained VBR. 1 Constrained VBR (default). This creates a maximum of one frame of buffering delay assuming a transport with a serialization speed of the nominal bitrate.
----	---	--

4.7 Generic CTLs

These macros are used with the `opus_decoder_ctl` and `opus_encoder_ctl` calls to generate a particular request.

Macros

- `#define OPUS_RESET_STATE`
Resets the codec state to be equivalent to a freshly initialized state.
- `#define OPUS_GET_FINAL_RANGE(x)`
Gets the final state of the codec's entropy coder.
- `#define OPUS_GET_BANDWIDTH(x)`
Gets the encoder's configured bandpass or the decoder's last bandpass.
- `#define OPUS_GET_SAMPLE_RATE(x)`
Gets the sampling rate the encoder or decoder was initialized with.
- `#define OPUS_SET_PHASE_INVERSION_DISABLED(x)`
If set to 1, disables the use of phase inversion for intensity stereo, improving the quality of mono downmixes, but slightly reducing normal stereo quality.
- `#define OPUS_GET_PHASE_INVERSION_DISABLED(x)`
Gets the encoder's configured phase inversion status.

4.7.1 Detailed Description

These macros are used with the `opus_decoder_ctl` and `opus_encoder_ctl` calls to generate a particular request. When called on an `OpusDecoder` they apply to that particular decoder instance. When called on an `OpusEncoder` they apply to the corresponding setting on that encoder instance, if present.

Some usage examples:

```
int ret;
opus_int32 pitch;
ret = opus_decoder_ctl(dec_ctx, OPUS_GET_PITCH(&
    pitch));
if (ret == OPUS_OK) return ret;

opus_encoder_ctl(enc_ctx, OPUS_RESET_STATE);
opus_decoder_ctl(dec_ctx, OPUS_RESET_STATE);

opus_int32 enc_bw, dec_bw;
opus_encoder_ctl(enc_ctx, OPUS_GET_BANDWIDTH(
    &enc_bw));
opus_decoder_ctl(dec_ctx, OPUS_GET_BANDWIDTH(
    &dec_bw));
if (enc_bw != dec_bw) {
    printf("packet bandwidth mismatch!\n");
}
```

See Also

[Opus Encoder](#), [opus_decoder_ctl](#), [opus_encoder_ctl](#), [Decoder related CTLs](#), [Encoder related CTLs](#)

4.7.2 Macro Definition Documentation

4.7.2.1 `#define OPUS_GET_BANDWIDTH(x)`

Gets the encoder's configured bandpass or the decoder's last bandpass.

See Also

[OPUS_SET_BANDWIDTH](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: OPUS_AUTO (default) OPUS_BANDWIDTH_NARROWBAND 4 kHz passband OPUS_BANDWIDTH_MEDIUMBAND 6 kHz passband OPUS_BANDWIDTH_WIDEBAND 8 kHz passband OPUS_BANDWIDTH_SUPERWIDEBAND 12 kHz passband OPUS_BANDWIDTH_FULLBAND 20 kHz passband
-----	---	--

4.7.2.2 #define OPUS_GET_FINAL_RANGE(x)

Gets the final state of the codec's entropy coder.

This is used for testing purposes, The encoder and decoder state should be identical after coding a payload (assuming no data corruption or software bugs)

Parameters

out	x	opus_uint32 *: Entropy coder state
-----	---	------------------------------------

4.7.2.3 #define OPUS_GET_PHASE_INVERSION_DISABLED(x)

Gets the encoder's configured phase inversion status.

See Also

[OPUS_SET_PHASE_INVERSION_DISABLED](#)

Parameters

out	x	opus_int32 *: Returns one of the following values: 0 Stereo phase inversion enabled (default). 1 Stereo phase inversion disabled.
-----	---	---

4.7.2.4 #define OPUS_GET_SAMPLE_RATE(x)

Gets the sampling rate the encoder or decoder was initialized with.

This simply returns the F_s value passed to [opus_encoder_init\(\)](#) or [opus_decoder_init\(\)](#).

Parameters

out	x	opus_int32 *: Sampling rate of encoder or decoder.
-----	---	--

4.7.2.5 #define OPUS_RESET_STATE

Resets the codec state to be equivalent to a freshly initialized state.

This should be called when switching streams in order to prevent the back to back decoding from giving different results from one at a time decoding.

4.7.2.6 #define OPUS_SET_PHASE_INVERSION_DISABLED(x)

If set to 1, disables the use of phase inversion for intensity stereo, improving the quality of mono downmixes, but slightly reducing normal stereo quality.

Disabling phase inversion in the decoder does not comply with RFC 6716, although it does not cause any interoperability issue and is expected to become part of the Opus standard once RFC 6716 is updated by draft-ietf-codec-opus-update.

See Also

[OPUS_GET_PHASE_INVERSION_DISABLED](#)

Parameters

in	x	opus_int32: Allowed values: 0 Enable phase inversion (default). 1 Disable phase inversion.
----	---	--

4.8 Decoder related CTLs

Macros

- `#define OPUS_SET_GAIN(x)`
Configures decoder gain adjustment.
- `#define OPUS_GET_GAIN(x)`
Gets the decoder's configured gain adjustment.
- `#define OPUS_GET_LAST_PACKET_DURATION(x)`
Gets the duration (in samples) of the last packet successfully decoded or concealed.
- `#define OPUS_GET_PITCH(x)`
Gets the pitch of the last decoded frame, if available.

4.8.1 Detailed Description

See Also

[Generic CTLs](#), [Encoder related CTLs](#), [Opus Decoder](#)

4.8.2 Macro Definition Documentation

4.8.2.1 `#define OPUS_GET_GAIN(x)`

Gets the decoder's configured gain adjustment.

See Also

[OPUS_SET_GAIN](#)

Parameters

out	x	opus_int32 *: Amount to scale PCM signal by in Q8 dB units.
-----	---	---

4.8.2.2 `#define OPUS_GET_LAST_PACKET_DURATION(x)`

Gets the duration (in samples) of the last packet successfully decoded or concealed.

Parameters

out	x	opus_int32 *: Number of samples (at current sampling rate).
-----	---	---

4.8.2.3 `#define OPUS_GET_PITCH(x)`

Gets the pitch of the last decoded frame, if available.

This can be used for any post-processing algorithm requiring the use of pitch, e.g. time stretching/shortening. If the last frame was not voiced, or if the pitch was not coded in the frame, then zero is returned.

This CTL is only implemented for decoder instances.

Parameters

out	x	opus_int32 *: pitch period at 48 kHz (or 0 if not available)
-----	---	--

4.8.2.4 #define OPUS_SET_GAIN(x)

Configures decoder gain adjustment.

Scales the decoded output by a factor specified in Q8 dB units. This has a maximum range of -32768 to 32767 inclusive, and returns OPUS_BAD_ARG otherwise. The default is zero indicating no adjustment. This setting survives decoder reset.

```
gain = pow(10, x/(20.0*256))
```

Parameters

in	x	opus_int32: Amount to scale PCM signal by in Q8 dB units.
----	---	---

4.9 Opus library information functions

Functions

- const char * [opus_strerror](#) (int error)
Converts an opus error code into a human readable string.
- const char * [opus_get_version_string](#) (void)
Gets the libopus version string.

4.9.1 Detailed Description

4.9.2 Function Documentation

4.9.2.1 const char* opus_get_version_string (void)

Gets the libopus version string.

Applications may look for the substring "-fixed" in the version string to determine whether they have a fixed-point or floating-point build at runtime.

Returns

Version string

4.9.2.2 const char* opus_strerror (int error)

Converts an opus error code into a human readable string.

Parameters

in	<i>error</i>	int: Error number
----	--------------	-------------------

Returns

Error string

4.10 Multistream specific encoder and decoder CTLs

These are convenience macros that are specific to the [opus_multistream_encoder_ctl\(\)](#) and [opus_multistream_decoder_ctl\(\)](#) interface.

Macros

- `#define OPUS_MULTISTREAM_GET_ENCODER_STATE(x, y)`
Gets the encoder state for an individual stream of a multistream encoder.
- `#define OPUS_MULTISTREAM_GET_DECODER_STATE(x, y)`
Gets the decoder state for an individual stream of a multistream decoder.

4.10.1 Detailed Description

These are convenience macros that are specific to the [opus_multistream_encoder_ctl\(\)](#) and [opus_multistream_decoder_ctl\(\)](#) interface. The CTLs from [Generic CTLs](#), [Encoder related CTLs](#), and [Decoder related CTLs](#) may be applied to a multistream encoder or decoder as well. In addition, you may retrieve the encoder or decoder state for an specific stream via [OPUS_MULTISTREAM_GET_ENCODER_STATE](#) or [OPUS_MULTISTREAM_GET_DECODER_STATE](#) and apply CTLs to it individually.

4.10.2 Macro Definition Documentation

4.10.2.1 `#define OPUS_MULTISTREAM_GET_DECODER_STATE(x, y)`

Gets the decoder state for an individual stream of a multistream decoder.

Parameters

in	x	opus_int32: The index of the stream whose decoder you wish to retrieve. This must be non-negative and less than the <code>streams</code> parameter used to initialize the decoder.
out	y	OpusDecoder**: Returns a pointer to the given decoder state.

Return values

<code>OPUS_BAD_ARG</code>	The index of the requested stream was out of range.
---------------------------	---

4.10.2.2 `#define OPUS_MULTISTREAM_GET_ENCODER_STATE(x, y)`

Gets the encoder state for an individual stream of a multistream encoder.

Parameters

in	x	opus_int32: The index of the stream whose encoder you wish to retrieve. This must be non-negative and less than the <code>streams</code> parameter used to initialize the encoder.
out	y	OpusEncoder**: Returns a pointer to the given encoder state.

Return values

<i>OPUS_BAD_ARG</i>	The index of the requested stream was out of range.
---------------------	---

4.11 Opus Multistream API

The multistream API allows individual Opus streams to be combined into a single packet, enabling support for up to 255 channels.

Typedefs

- typedef struct [OpusMSEncoder](#) [OpusMSEncoder](#)
Opus multistream encoder state.
- typedef struct [OpusMSDecoder](#) [OpusMSDecoder](#)
Opus multistream decoder state.

Multistream encoder functions

- [opus_int32 opus_multistream_encoder_get_size](#) (int streams, int coupled_streams)
Gets the size of an OpusMSEncoder structure.
- [opus_int32 opus_multistream_surround_encoder_get_size](#) (int channels, int mapping_family)
- [OpusMSEncoder * opus_multistream_encoder_create](#) ([opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int application, int *error)
Allocates and initializes a multistream encoder state.
- [OpusMSEncoder * opus_multistream_surround_encoder_create](#) ([opus_int32](#) Fs, int channels, int mapping_family, int *streams, int *coupled_streams, unsigned char *mapping, int application, int *error)
- int [opus_multistream_encoder_init](#) ([OpusMSEncoder](#) *st, [opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int application)
Initialize a previously allocated multistream encoder state.
- int [opus_multistream_surround_encoder_init](#) ([OpusMSEncoder](#) *st, [opus_int32](#) Fs, int channels, int mapping_family, int *streams, int *coupled_streams, unsigned char *mapping, int application)
- int [opus_multistream_encode](#) ([OpusMSEncoder](#) *st, const [opus_int16](#) *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes a multistream Opus frame.
- int [opus_multistream_encode_float](#) ([OpusMSEncoder](#) *st, const float *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes a multistream Opus frame from floating point input.
- void [opus_multistream_encoder_destroy](#) ([OpusMSEncoder](#) *st)
Frees an OpusMSEncoder allocated by opus_multistream_encoder_create().
- int [opus_multistream_encoder_ctl](#) ([OpusMSEncoder](#) *st, int request,...)
Perform a CTL function on a multistream Opus encoder.

Multistream decoder functions

- [opus_int32 opus_multistream_decoder_get_size](#) (int streams, int coupled_streams)
Gets the size of an OpusMSDecoder structure.
- [OpusMSDecoder * opus_multistream_decoder_create](#) ([opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int *error)
Allocates and initializes a multistream decoder state.
- int [opus_multistream_decoder_init](#) ([OpusMSDecoder](#) *st, [opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping)
Initialize a previously allocated decoder state object.

- int `opus_multistream_decode` (`OpusMSDecoder *st`, const unsigned char *data, `opus_int32` len, `opus_int16 *pcm`, int frame_size, int decode_fec)
Decode a multistream Opus packet.
- int `opus_multistream_decode_float` (`OpusMSDecoder *st`, const unsigned char *data, `opus_int32` len, float *pcm, int frame_size, int decode_fec)
Decode a multistream Opus packet with floating point output.
- int `opus_multistream_decoder_ctl` (`OpusMSDecoder *st`, int request,...)
Perform a CTL function on a multistream Opus decoder.
- void `opus_multistream_decoder_destroy` (`OpusMSDecoder *st`)
Frees an `OpusMSDecoder` allocated by `opus_multistream_decoder_create()`.

4.11.1 Detailed Description

The multistream API allows individual Opus streams to be combined into a single packet, enabling support for up to 255 channels. Unlike an elementary Opus stream, the encoder and decoder must negotiate the channel configuration before the decoder can successfully interpret the data in the packets produced by the encoder. Some basic information, such as packet duration, can be computed without any special negotiation.

The format for multistream Opus packets is defined in [RFC 7845](#) and is based on the self-delimited Opus framing described in Appendix B of [RFC 6716](#). Normal Opus packets are just a degenerate case of multistream Opus packets, and can be encoded or decoded with the multistream API by setting `streams` to 1 when initializing the encoder or decoder.

Multistream Opus streams can contain up to 255 elementary Opus streams. These may be either "uncoupled" or "coupled", indicating that the decoder is configured to decode them to either 1 or 2 channels, respectively. The streams are ordered so that all coupled streams appear at the beginning.

A mapping table defines which decoded channel i should be used for each input/output (I/O) channel j . This table is typically provided as an unsigned char array. Let $i = \text{mapping}[j]$ be the index for I/O channel j . If $i < 2 * \text{coupled_streams}$, then I/O channel j is encoded as the left channel of stream $(i/2)$ if i is even, or as the right channel of stream $(i/2)$ if i is odd. Otherwise, I/O channel j is encoded as mono in stream $(i - \text{coupled_streams})$, unless it has the special value 255, in which case it is omitted from the encoding entirely (the decoder will reproduce it as silence). Each value i must either be the special value 255 or be less than $\text{streams} + \text{coupled_streams}$.

The output channels specified by the encoder should use the [Vorbis channel ordering](#). A decoder may wish to apply an additional permutation to the mapping the encoder used to achieve a different output channel order (e.g. for outputting in WAV order).

Each multistream packet contains an Opus packet for each stream, and all of the Opus packets in a single multistream packet must have the same duration. Therefore the duration of a multistream packet can be extracted from the TOC sequence of the first stream, which is located at the beginning of the packet, just like an elementary Opus stream:

```
int nb_samples;
int nb_frames;
nb_frames = opus_packet_get_nb_frames(data, len);
if (nb_frames < 1)
    return nb_frames;
nb_samples = opus_packet_get_samples_per_frame(
    data, 48000) * nb_frames;
```

The general encoding and decoding process proceeds exactly the same as in the normal [Opus Encoder](#) and [Opus Decoder](#) APIs. See their documentation for an overview of how to use the corresponding multistream functions.

4.11.2 Typedef Documentation

4.11.2.1 typedef struct OpusMSDecoder OpusMSDecoder

Opus multistream decoder state.

This contains the complete state of a multistream Opus decoder. It is position independent and can be freely copied.

See Also

[opus_multistream_decoder_create](#)
[opus_multistream_decoder_init](#)

4.11.2.2 typedef struct OpusMSEncoder OpusMSEncoder

Opus multistream encoder state.

This contains the complete state of a multistream Opus encoder. It is position independent and can be freely copied.

See Also

[opus_multistream_encoder_create](#)
[opus_multistream_encoder_init](#)

4.11.3 Function Documentation

4.11.3.1 int opus_multistream_decode (OpusMSDecoder * *st*, const unsigned char * *data*, opus_int32 *len*, opus_int16 * *pcm*, int *frame_size*, int *decode_fec*)

Decode a multistream Opus packet.

Parameters

	<i>st</i>	OpusMSDecoder*: Multistream decoder state.
in	<i>data</i>	const unsigned char*: Input payload. Use a NULL pointer to indicate packet loss.
	<i>len</i>	opus_int32: Number of bytes in payload.
out	<i>pcm</i>	opus_int16*: Output signal, with interleaved samples. This must contain room for <i>frame_size</i> * <i>channels</i> samples.
	<i>frame_size</i>	int: The number of samples per channel of available space in <i>pcm</i> . If this is less than the maximum packet duration (120 ms; 5760 for 48kHz), this function will not be capable of decoding some packets. In the case of PLC (<i>data</i> ==NULL) or FEC (<i>decode_fec</i> =1), then <i>frame_size</i> needs to be exactly the duration of audio that is missing, otherwise the decoder will not be in the optimal state to decode the next incoming packet. For the PLC and FEC cases, <i>frame_size</i> must be a multiple of 2.5 ms.
	<i>decode_fec</i>	int: Flag (0 or 1) to request that any in-band forward error correction data be decoded. If no such data is available, the frame is decoded as if it were lost.

Returns

Number of samples decoded on success or a negative error code (see [Error codes](#)) on failure.

4.11.3.2 `int opus_multistream_decode_float (OpusMSDecoder * st, const unsigned char * data, opus_int32 len, float * pcm, int frame_size, int decode_fec)`

Decode a multistream Opus packet with floating point output.

Parameters

	<i>st</i>	OpusMSDecoder*: Multistream decoder state.
in	<i>data</i>	const unsigned char*: Input payload. Use a NULL pointer to indicate packet loss.
	<i>len</i>	opus_int32: Number of bytes in payload.
out	<i>pcm</i>	opus_int16*: Output signal, with interleaved samples. This must contain room for <code>frame_size*channels</code> samples.
	<i>frame_size</i>	int: The number of samples per channel of available space in <i>pcm</i> . If this is less than the maximum packet duration (120 ms; 5760 for 48kHz), this function will not be capable of decoding some packets. In the case of PLC (<code>data==NULL</code>) or FEC (<code>decode_fec=1</code>), then <code>frame_size</code> needs to be exactly the duration of audio that is missing, otherwise the decoder will not be in the optimal state to decode the next incoming packet. For the PLC and FEC cases, <code>frame_size</code> must be a multiple of 2.5 ms.
	<i>decode_fec</i>	int: Flag (0 or 1) to request that any in-band forward error correction data be decoded. If no such data is available, the frame is decoded as if it were lost.

Returns

Number of samples decoded on success or a negative error code (see [Error codes](#)) on failure.

4.11.3.3 `OpusMSDecoder* opus_multistream_decoder_create (opus_int32 Fs, int channels, int streams, int coupled_streams, const unsigned char * mapping, int * error)`

Allocates and initializes a multistream decoder state.

Call `opus_multistream_decoder_destroy()` to release this object when finished.

Parameters

	<i>Fs</i>	opus_int32: Sampling rate to decode at (in Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
	<i>channels</i>	int: Number of channels to output. This must be at most 255. It may be different from the number of coded channels (<code>streams + coupled_streams</code>).
	<i>streams</i>	int: The total number of streams coded in the input. This must be no more than 255.
	<i>coupled_streams</i>	int: Number of streams to decode as coupled (2 channel) streams. This must be no larger than the total number of streams. Additionally, The total number of coded channels (<code>streams + coupled_streams</code>) must be no more than 255.
in	<i>mapping</i>	const unsigned char[channels]: Mapping from coded channels to output channels, as described in Opus Multistream API .
out	<i>error</i>	int *: Returns <code>OPUS_OK</code> on success, or an error code (see Error codes) on failure.

4.11.3.4 `int opus_multistream_decoder_ctl (OpusMSDecoder * st, int request, ...)`

Perform a CTL function on a multistream Opus decoder.

Generally the request and subsequent arguments are generated by a convenience macro.

Parameters

<i>st</i>	OpusMSDecoder*: Multistream decoder state.
<i>request</i>	This and all remaining parameters should be replaced by one of the convenience macros in Generic CTLs , Decoder related CTLs , or Multistream specific encoder and decoder CTLs .

See Also

[Generic CTLs](#)

[Decoder related CTLs](#)

[Multistream specific encoder and decoder CTLs](#)

4.11.3.5 `void opus_multistream_decoder_destroy (OpusMSDecoder * st)`

Frees an OpusMSDecoder allocated by [opus_multistream_decoder_create\(\)](#).

Parameters

<i>st</i>	OpusMSDecoder: Multistream decoder state to be freed.
-----------	---

4.11.3.6 `opus_int32 opus_multistream_decoder_get_size (int streams, int coupled_streams)`

Gets the size of an OpusMSDecoder structure.

Parameters

<i>streams</i>	<code>int</code> : The total number of streams coded in the input. This must be no more than 255.
<i>coupled_streams</i>	<code>int</code> : Number streams to decode as coupled (2 channel) streams. This must be no larger than the total number of streams. Additionally, The total number of coded channels (<code>streams + coupled_streams</code>) must be no more than 255.

Returns

The size in bytes on success, or a negative error code (see [Error codes](#)) on error.

4.11.3.7 `int opus_multistream_decoder_init (OpusMSDecoder * st, opus_int32 Fs, int channels, int streams, int coupled_streams, const unsigned char * mapping)`

Initialize a previously allocated decoder state object.

The memory pointed to by *st* must be at least the size returned by [opus_multistream_encoder_get_size\(\)](#). This is intended for applications which use their own allocator instead of malloc. To reset a previously initialized state, use the [OPUS_RESET_STATE](#) CTL.

See Also

[opus_multistream_decoder_create](#)
[opus_multistream_decoder_get_size](#)

Parameters

	<i>st</i>	OpusMSEncoder*: Multistream encoder state to initialize.
	<i>Fs</i>	opus_int32: Sampling rate to decode at (in Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
	<i>channels</i>	int: Number of channels to output. This must be at most 255. It may be different from the number of coded channels (<i>streams</i> + <i>coupled_streams</i>).
	<i>streams</i>	int: The total number of streams coded in the input. This must be no more than 255.
	<i>coupled_streams</i>	int: Number of streams to decode as coupled (2 channel) streams. This must be no larger than the total number of streams. Additionally, The total number of coded channels (<i>streams</i> + <i>coupled_streams</i>) must be no more than 255.
in	<i>mapping</i>	const unsigned char[channels]: Mapping from coded channels to output channels, as described in Opus Multistream API .

Returns

OPUS_OK on success, or an error code (see [Error codes](#)) on failure.

4.11.3.8 int opus_multistream_encode (OpusMSEncoder * *st*, const opus_int16 * *pcm*, int *frame_size*, unsigned char * *data*, opus_int32 *max_data_bytes*)

Encodes a multistream Opus frame.

Parameters

	<i>st</i>	OpusMSEncoder*: Multistream encoder state.
in	<i>pcm</i>	const opus_int16*: The input signal as interleaved samples. This must contain <i>frame_size</i> * <i>channels</i> samples.
	<i>frame_size</i>	int: Number of samples per channel in the input signal. This must be an Opus frame size for the encoder's sampling rate. For example, at 48 kHz the permitted values are 120, 240, 480, 960, 1920, and 2880. Passing in a duration of less than 10 ms (480 samples at 48 kHz) will prevent the encoder from using the LPC or hybrid modes.
out	<i>data</i>	unsigned char*: Output payload. This must contain storage for at least <i>max_data_bytes</i> .
in	<i>max_data_bytes</i>	opus_int32: Size of the allocated memory for the output payload. This may be used to impose an upper limit on the instant bitrate, but should not be used as the only bitrate control. Use OPUS_SET_BITRATE to control the bitrate.

Returns

The length of the encoded packet (in bytes) on success or a negative error code (see [Error codes](#)) on failure.

4.11.3.9 `int opus_multistream_encode_float (OpusMSEncoder * st, const float * pcm, int frame_size, unsigned char * data, opus_int32 max_data_bytes)`

Encodes a multistream Opus frame from floating point input.

Parameters

	<i>st</i>	OpusMSEncoder*: Multistream encoder state.
in	<i>pcm</i>	const float*: The input signal as interleaved samples with a normal range of +/-1.0. Samples with a range beyond +/-1.0 are supported but will be clipped by decoders using the integer API and should only be used if it is known that the far end supports extended dynamic range. This must contain <code>frame_size*channels</code> samples.
	<i>frame_size</i>	int: Number of samples per channel in the input signal. This must be an Opus frame size for the encoder's sampling rate. For example, at 48 kHz the permitted values are 120, 240, 480, 960, 1920, and 2880. Passing in a duration of less than 10 ms (480 samples at 48 kHz) will prevent the encoder from using the LPC or hybrid modes.
out	<i>data</i>	unsigned char*: Output payload. This must contain storage for at least <code>max_data_bytes</code> .
in	<i>max_data_bytes</i>	opus_int32: Size of the allocated memory for the output payload. This may be used to impose an upper limit on the instant bitrate, but should not be used as the only bitrate control. Use OPUS_SET_BITRATE to control the bitrate.

Returns

The length of the encoded packet (in bytes) on success or a negative error code (see [Error codes](#)) on failure.

4.11.3.10 `OpusMSEncoder* opus_multistream_encoder_create (opus_int32 Fs, int channels, int streams, int coupled_streams, const unsigned char * mapping, int application, int * error)`

Allocates and initializes a multistream encoder state.

Call [opus_multistream_encoder_destroy\(\)](#) to release this object when finished.

Parameters

	<i>Fs</i>	opus_int32: Sampling rate of the input signal (in Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
	<i>channels</i>	int: Number of channels in the input signal. This must be at most 255. It may be greater than the number of coded channels (<code>streams + coupled_streams</code>).
	<i>streams</i>	int: The total number of streams to encode from the input. This must be no more than the number of channels.
	<i>coupled_streams</i>	int: Number of coupled (2 channel) streams to encode. This must be no larger than the total number of streams. Additionally, The total number of encoded channels (<code>streams + coupled_streams</code>) must be no more than the number of input channels.

in	<i>mapping</i>	const unsigned char[channels]: Mapping from encoded channels to input channels, as described in Opus Multistream API . As an extra constraint, the multistream encoder does not allow encoding coupled streams for which one channel is unused since this is never a good idea.
	<i>application</i>	int: The target encoder application. This must be one of the following: OPUS_APPLICATION_VOIP Process signal for improved speech intelligibility. OPUS_APPLICATION_AUDIO Favor faithfulness to the original input. OPUS_APPLICATION_RESTRICTED_LOWDELAY Configure the minimum possible coding delay by disabling certain modes of operation.
out	<i>error</i>	int *: Returns OPUS_OK on success, or an error code (see Error codes) on failure.

4.11.3.11 int opus_multistream_encoder_ctl (OpusMSEncoder * st, int request, ...)

Perform a CTL function on a multistream Opus encoder.

Generally the request and subsequent arguments are generated by a convenience macro.

Parameters

<i>st</i>	OpusMSEncoder*: Multistream encoder state.
<i>request</i>	This and all remaining parameters should be replaced by one of the convenience macros in Generic CTLs , Encoder related CTLs , or Multistream specific encoder and decoder CTLs .

See Also

[Generic CTLs](#)
[Encoder related CTLs](#)
[Multistream specific encoder and decoder CTLs](#)

4.11.3.12 void opus_multistream_encoder_destroy (OpusMSEncoder * st)

Frees an OpusMSEncoder allocated by [opus_multistream_encoder_create\(\)](#).

Parameters

<i>st</i>	OpusMSEncoder*: Multistream encoder state to be freed.
-----------	--

4.11.3.13 opus_int32 opus_multistream_encoder_get_size (int streams, int coupled_streams)

Gets the size of an OpusMSEncoder structure.

Parameters

<i>streams</i>	int: The total number of streams to encode from the input. This must be no more than 255.
<i>coupled_streams</i>	int: Number of coupled (2 channel) streams to encode. This must be no larger than the total number of streams. Additionally, The total number of encoded channels (<i>streams</i> + <i>coupled_streams</i>) must be no more than 255.

Returns

The size in bytes on success, or a negative error code (see [Error codes](#)) on error.

4.11.3.14 `int opus_multistream_encoder_init (OpusMSEncoder * st, opus_int32 Fs, int channels, int streams, int coupled_streams, const unsigned char * mapping, int application)`

Initialize a previously allocated multistream encoder state.

The memory pointed to by *st* must be at least the size returned by `opus_multistream_encoder_get_size()`. This is intended for applications which use their own allocator instead of `malloc`. To reset a previously initialized state, use the `OPUS_RESET_STATE` CTL.

See Also

[opus_multistream_encoder_create](#)
[opus_multistream_encoder_get_size](#)

Parameters

	<i>st</i>	OpusMSEncoder*: Multistream encoder state to initialize.
	<i>Fs</i>	opus_int32: Sampling rate of the input signal (in Hz). This must be one of 8000, 12000, 16000, 24000, or 48000.
	<i>channels</i>	int: Number of channels in the input signal. This must be at most 255. It may be greater than the number of coded channels (<code>streams + coupled_streams</code>).
	<i>streams</i>	int: The total number of streams to encode from the input. This must be no more than the number of channels.
	<i>coupled_streams</i>	int: Number of coupled (2 channel) streams to encode. This must be no larger than the total number of streams. Additionally, The total number of encoded channels (<code>streams + coupled_streams</code>) must be no more than the number of input channels.
in	<i>mapping</i>	const unsigned char[channels]: Mapping from encoded channels to input channels, as described in Opus Multistream API . As an extra constraint, the multistream encoder does not allow encoding coupled streams for which one channel is unused since this is never a good idea.
	<i>application</i>	int: The target encoder application. This must be one of the following: OPUS_APPLICATION_VOIP Process signal for improved speech intelligibility. OPUS_APPLICATION_AUDIO Favor faithfulness to the original input. OPUS_APPLICATION_RESTRICTED_LOWDELAY Configure the minimum possible coding delay by disabling certain modes of operation.

Returns

`OPUS_OK` on success, or an error code (see [Error codes](#)) on failure.

4.11.3.15 `OpusMSEncoder* opus_multistream_surround_encoder_create (opus_int32 Fs, int channels, int mapping_family, int * streams, int * coupled_streams, unsigned char * mapping, int application, int * error)`

4.11.3.16 `opus_int32 opus_multistream_surround_encoder_get_size (int channels, int mapping_family)`

4.11.3.17 int opus_multistream_surround_encoder_init (OpusMSEncoder * st, opus_int32 Fs, int channels, int mapping_family, int * streams, int * coupled_streams, unsigned char * mapping, int application)

4.12 Opus Custom

Opus Custom is an optional part of the Opus specification and reference implementation which uses a distinct API from the regular API and supports frame sizes that are not normally supported. Use of Opus Custom is discouraged for all but very special applications for which a frame size different from 2.5, 5, 10, or 20 ms is needed (for either complexity or latency reasons) and where interoperability is less important.

Typedefs

- typedef struct [OpusCustomEncoder](#) [OpusCustomEncoder](#)
Contains the state of an encoder.
- typedef struct [OpusCustomDecoder](#) [OpusCustomDecoder](#)
State of the decoder.
- typedef struct [OpusCustomMode](#) [OpusCustomMode](#)
The mode contains all the information necessary to create an encoder.

Functions

- [OpusCustomMode](#) * [opus_custom_mode_create](#) ([opus_int32](#) Fs, int frame_size, int *error)
Creates a new mode struct.
- void [opus_custom_mode_destroy](#) ([OpusCustomMode](#) *mode)
Destroys a mode struct.
- int [opus_custom_encoder_get_size](#) (const [OpusCustomMode](#) *mode, int channels)
Gets the size of an OpusCustomEncoder structure.
- [OpusCustomEncoder](#) * [opus_custom_encoder_create](#) (const [OpusCustomMode](#) *mode, int channels, int *error)
Creates a new encoder state.
- void [opus_custom_encoder_destroy](#) ([OpusCustomEncoder](#) *st)
Destroys a an encoder state.
- int [opus_custom_encode_float](#) ([OpusCustomEncoder](#) *st, const float *pcm, int frame_size, unsigned char *compressed, int maxCompressedBytes)
Encodes a frame of audio.
- int [opus_custom_encode](#) ([OpusCustomEncoder](#) *st, const [opus_int16](#) *pcm, int frame_size, unsigned char *compressed, int maxCompressedBytes)
Encodes a frame of audio.
- int [opus_custom_encoder_ctl](#) ([OpusCustomEncoder](#) *OPUS_RESTRICT st, int request,...)
Perform a CTL function on an Opus custom encoder.
- int [opus_custom_decoder_get_size](#) (const [OpusCustomMode](#) *mode, int channels)
Gets the size of an OpusCustomDecoder structure.
- int [opus_custom_decoder_init](#) ([OpusCustomDecoder](#) *st, const [OpusCustomMode](#) *mode, int channels)
Initializes a previously allocated decoder state The memory pointed to by st must be the size returned by opus_custom_decoder_get_size.
- [OpusCustomDecoder](#) * [opus_custom_decoder_create](#) (const [OpusCustomMode](#) *mode, int channels, int *error)
Creates a new decoder state.
- void [opus_custom_decoder_destroy](#) ([OpusCustomDecoder](#) *st)
Destroys a an decoder state.

- int [opus_custom_decode_float](#) ([OpusCustomDecoder](#) *st, const unsigned char *data, int len, float *pcm, int frame_size)
Decode an opus custom frame with floating point output.
- int [opus_custom_decode](#) ([OpusCustomDecoder](#) *st, const unsigned char *data, int len, [opus_int16](#) *pcm, int frame_size)
Decode an opus custom frame.
- int [opus_custom_decoder_ctl](#) ([OpusCustomDecoder](#) *OPUS_RESTRICT st, int request,...)
Perform a CTL function on an Opus custom decoder.

4.12.1 Detailed Description

Opus Custom is an optional part of the Opus specification and reference implementation which uses a distinct API from the regular API and supports frame sizes that are not normally supported. Use of Opus Custom is discouraged for all but very special applications for which a frame size different from 2.5, 5, 10, or 20 ms is needed (for either complexity or latency reasons) and where interoperability is less important. In addition to the interoperability limitations the use of Opus custom disables a substantial chunk of the codec and generally lowers the quality available at a given bitrate. Normally when an application needs a different frame size from the codec it should buffer to match the sizes but this adds a small amount of delay which may be important in some very low latency applications. Some transports (especially constant rate RF transports) may also work best with frames of particular durations.

Libopus only supports custom modes if they are enabled at compile time.

The Opus Custom API is similar to the regular API but the [opus_encoder_create](#) and [opus_decoder_create](#) calls take an additional mode parameter which is a structure produced by a call to [opus_custom_mode_create](#). Both the encoder and decoder must create a mode using the same sample rate (fs) and frame size (frame size) so these parameters must either be signaled out of band or fixed in a particular implementation.

Similar to regular Opus the custom modes support on the fly frame size switching, but the sizes available depend on the particular frame size in use. For some initial frame sizes on a single on the fly size is available.

4.12.2 Typedef Documentation

4.12.2.1 typedef struct [OpusCustomDecoder](#) [OpusCustomDecoder](#)

State of the decoder.

One decoder state is needed for each stream. It is initialized once at the beginning of the stream. Do *not* re-initialize the state for every frame. Decoder state

4.12.2.2 typedef struct [OpusCustomEncoder](#) [OpusCustomEncoder](#)

Contains the state of an encoder.

One encoder state is needed for each stream. It is initialized once at the beginning of the stream. Do *not* re-initialize the state for every frame. Encoder state

4.12.2.3 typedef struct [OpusCustomMode](#) [OpusCustomMode](#)

The mode contains all the information necessary to create an encoder.

Both the encoder and decoder need to be initialized with exactly the same mode, otherwise the output will be corrupted. Mode configuration

4.12.3 Function Documentation

4.12.3.1 `int opus_custom_decode (OpusCustomDecoder * st, const unsigned char * data, int len, opus_int16 * pcm, int frame_size)`

Decode an opus custom frame.

Parameters

in	<i>st</i>	OpusCustomDecoder*: Decoder state
in	<i>data</i>	char*: Input payload. Use a NULL pointer to indicate packet loss
in	<i>len</i>	int: Number of bytes in payload
out	<i>pcm</i>	opus_int16*: Output signal (interleaved if 2 channels). length is frame_size*channels*sizeof(opus_int16)
in	<i>frame_size</i>	Number of samples per channel of available space in *pcm.

Returns

Number of decoded samples or [Error codes](#)

4.12.3.2 `int opus_custom_decode_float (OpusCustomDecoder * st, const unsigned char * data, int len, float * pcm, int frame_size)`

Decode an opus custom frame with floating point output.

Parameters

in	<i>st</i>	OpusCustomDecoder*: Decoder state
in	<i>data</i>	char*: Input payload. Use a NULL pointer to indicate packet loss
in	<i>len</i>	int: Number of bytes in payload
out	<i>pcm</i>	float*: Output signal (interleaved if 2 channels). length is frame_size*channels*sizeof(float)
in	<i>frame_size</i>	Number of samples per channel of available space in *pcm.

Returns

Number of decoded samples or [Error codes](#)

4.12.3.3 `OpusCustomDecoder* opus_custom_decoder_create (const OpusCustomMode * mode, int channels, int * error)`

Creates a new decoder state.

Each stream needs its own decoder state (can't be shared across simultaneous streams).

Parameters

in	<i>mode</i>	OpusCustomMode: Contains all the information about the characteristics of the stream (must be the same characteristics as used for the encoder)
in	<i>channels</i>	int: Number of channels
out	<i>error</i>	int*: Returns an error code

Returns

Newly created decoder state.

4.12.3.4 `int opus_custom_decoder_ctl (OpusCustomDecoder *OPUS_RESTRICT st, int request, ...)`

Perform a CTL function on an Opus custom decoder.

Generally the request and subsequent arguments are generated by a convenience macro.

See Also

[Generic CTLs](#)

4.12.3.5 `void opus_custom_decoder_destroy (OpusCustomDecoder * st)`

Destroys a an decoder state.

Parameters

in	<i>st</i>	OpusCustomDecoder*: State to be freed.
----	-----------	--

4.12.3.6 `int opus_custom_decoder_get_size (const OpusCustomMode * mode, int channels)`

Gets the size of an OpusCustomDecoder structure.

Parameters

in	<i>mode</i>	OpusCustomMode *: Mode configuration
in	<i>channels</i>	int: Number of channels

Returns

size

4.12.3.7 `int opus_custom_decoder_init (OpusCustomDecoder * st, const OpusCustomMode * mode, int channels)`

Initializes a previously allocated decoder state The memory pointed to by st must be the size returned by opus_custom_decoder_get_size.

This is intended for applications which use their own allocator instead of malloc.

See Also

[opus_custom_decoder_create\(\)](#),[opus_custom_decoder_get_size\(\)](#) To reset a previously initialized state use the `OPUS_RESET_STATE` CTL.

Parameters

in	<i>st</i>	OpusCustomDecoder*: Decoder state
in	<i>mode</i>	OpusCustomMode *: Contains all the information about the characteristics of the stream (must be the same characteristics as used for the encoder)
in	<i>channels</i>	int: Number of channels

Returns

OPUS_OK Success or [Error codes](#)

4.12.3.8 `int opus_custom_encode (OpusCustomEncoder * st, const opus_int16 * pcm, int frame_size, unsigned char * compressed, int maxCompressedBytes)`

Encodes a frame of audio.

Parameters

in	<i>st</i>	OpusCustomEncoder*: Encoder state
in	<i>pcm</i>	opus_int16*: PCM audio in signed 16-bit format (native endian). There must be exactly frame_size samples per channel.
in	<i>frame_size</i>	int: Number of samples per frame of input signal
out	<i>compressed</i>	char *: The compressed data is written here. This may not alias pcm and must be at least maxCompressedBytes long.
in	<i>max-Compressed-Bytes</i>	int: Maximum number of bytes to use for compressing the frame (can change from one frame to another)

Returns

Number of bytes written to "compressed". If negative, an error has occurred (see error codes). It is IMPORTANT that the length returned be somehow transmitted to the decoder. Otherwise, no decoding is possible.

4.12.3.9 `int opus_custom_encode_float (OpusCustomEncoder * st, const float * pcm, int frame_size, unsigned char * compressed, int maxCompressedBytes)`

Encodes a frame of audio.

Parameters

in	<i>st</i>	OpusCustomEncoder*: Encoder state
in	<i>pcm</i>	float*: PCM audio in float format, with a normal range of +/-1.0. Samples with a range beyond +/-1.0 are supported but will be clipped by decoders using the integer API and should only be used if it is known that the far end supports extended dynamic range. There must be exactly frame_size samples per channel.
in	<i>frame_size</i>	int: Number of samples per frame of input signal
out	<i>compressed</i>	char *: The compressed data is written here. This may not alias pcm and must be at least maxCompressedBytes long.
in	<i>max-Compressed-Bytes</i>	int: Maximum number of bytes to use for compressing the frame (can change from one frame to another)

Returns

Number of bytes written to "compressed". If negative, an error has occurred (see error codes). It is IMPORTANT that the length returned be somehow transmitted to the decoder. Otherwise, no decoding is possible.

4.12.3.10 `OpusCustomEncoder*` `opus_custom_encoder_create` (`const OpusCustomMode *` *mode*, `int` *channels*, `int *` *error*)

Creates a new encoder state.

Each stream needs its own encoder state (can't be shared across simultaneous streams).

Parameters

in	<i>mode</i>	OpusCustomMode*: Contains all the information about the characteristics of the stream (must be the same characteristics as used for the decoder)
in	<i>channels</i>	int: Number of channels
out	<i>error</i>	int*: Returns an error code

Returns

Newly created encoder state.

4.12.3.11 `int` `opus_custom_encoder_ctl` (`OpusCustomEncoder *` *OPUS_RESTRICT st*, `int` *request*, ...)

Perform a CTL function on an Opus custom encoder.

Generally the request and subsequent arguments are generated by a convenience macro.

See Also

[Encoder related CTLs](#)

4.12.3.12 `void` `opus_custom_encoder_destroy` (`OpusCustomEncoder *` *st*)

Destroys a an encoder state.

Parameters

in	<i>st</i>	OpusCustomEncoder*: State to be freed.
----	-----------	--

4.12.3.13 `int` `opus_custom_encoder_get_size` (`const OpusCustomMode *` *mode*, `int` *channels*)

Gets the size of an OpusCustomEncoder structure.

Parameters

in	<i>mode</i>	OpusCustomMode *: Mode configuration
in	<i>channels</i>	int: Number of channels

Returns

size

4.12.3.14 `OpusCustomMode*` `opus_custom_mode_create (opus_int32 Fs, int frame_size, int * error)`

Creates a new mode struct.

This will be passed to an encoder or decoder. The mode **MUST NOT BE DESTROYED** until the encoders and decoders that use it are destroyed as well.

Parameters

in	<i>Fs</i>	int: Sampling rate (8000 to 96000 Hz)
in	<i>frame_size</i>	int: Number of samples (per channel) to encode in each packet (64 - 1024, prime factorization must contain zero or more 2s, 3s, or 5s and no other primes)
out	<i>error</i>	int*: Returned error code (if NULL, no error will be returned)

Returns

A newly created mode

4.12.3.15 `void opus_custom_mode_destroy (OpusCustomMode * mode)`

Destroys a mode struct.

Only call this after all encoders and decoders using this mode are destroyed as well.

Parameters

in	<i>mode</i>	OpusCustomMode*: Mode to be freed.
----	-------------	------------------------------------

Chapter 5

File Documentation

5.1 opus.h File Reference

Opus reference implementation API.

```
#include "opus_types.h"  
#include "opus_defines.h"
```

Typedefs

- typedef struct [OpusEncoder](#) [OpusEncoder](#)
Opus encoder state.
- typedef struct [OpusDecoder](#) [OpusDecoder](#)
Opus decoder state.
- typedef struct [OpusRepacketizer](#) [OpusRepacketizer](#)

Functions

- int [opus_encoder_get_size](#) (int channels)
Gets the size of an [OpusEncoder](#) structure.
- [OpusEncoder](#) * [opus_encoder_create](#) ([opus_int32](#) Fs, int channels, int application, int *error)
Allocates and initializes an encoder state.
- int [opus_encoder_init](#) ([OpusEncoder](#) *st, [opus_int32](#) Fs, int channels, int application)
Initializes a previously allocated encoder state The memory pointed to by st must be at least the size returned by [opus_encoder_get_size](#)().
- [opus_int32](#) [opus_encode](#) ([OpusEncoder](#) *st, const [opus_int16](#) *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes an Opus frame.
- [opus_int32](#) [opus_encode_float](#) ([OpusEncoder](#) *st, const float *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes an Opus frame from floating point input.
- void [opus_encoder_destroy](#) ([OpusEncoder](#) *st)
Frees an [OpusEncoder](#) allocated by [opus_encoder_create](#)().
- int [opus_encoder_ctl](#) ([OpusEncoder](#) *st, int request,...)

- Perform a CTL function on an Opus encoder.*

 - int `opus_decoder_get_size` (int channels)

Gets the size of an `OpusDecoder` structure.
- `OpusDecoder * opus_decoder_create` (`opus_int32` Fs, int channels, int *error)
- Allocates and initializes a decoder state.*
- int `opus_decoder_init` (`OpusDecoder *st`, `opus_int32` Fs, int channels)
- Initializes a previously allocated decoder state.*
- int `opus_decode` (`OpusDecoder *st`, const unsigned char *data, `opus_int32` len, `opus_int16` *pcm, int frame_size, int decode_fec)
- Decode an Opus packet.*
- int `opus_decode_float` (`OpusDecoder *st`, const unsigned char *data, `opus_int32` len, float *pcm, int frame_size, int decode_fec)
- Decode an Opus packet with floating point output.*
- int `opus_decoder_ctl` (`OpusDecoder *st`, int request,...)
- Perform a CTL function on an Opus decoder.*
- void `opus_decoder_destroy` (`OpusDecoder *st`)
- Frees an `OpusDecoder` allocated by `opus_decoder_create()`.*
- int `opus_packet_parse` (const unsigned char *data, `opus_int32` len, unsigned char *out_toc, const unsigned char *frames[48], `opus_int16` size[48], int *payload_offset)
- Parse an opus packet into one or more frames.*
- int `opus_packet_get_bandwidth` (const unsigned char *data)
- Gets the bandwidth of an Opus packet.*
- int `opus_packet_get_samples_per_frame` (const unsigned char *data, `opus_int32` Fs)
- Gets the number of samples per frame from an Opus packet.*
- int `opus_packet_get_nb_channels` (const unsigned char *data)
- Gets the number of channels from an Opus packet.*
- int `opus_packet_get_nb_frames` (const unsigned char packet[], `opus_int32` len)
- Gets the number of frames in an Opus packet.*
- int `opus_packet_get_nb_samples` (const unsigned char packet[], `opus_int32` len, `opus_int32` Fs)
- Gets the number of samples of an Opus packet.*
- int `opus_decoder_get_nb_samples` (const `OpusDecoder *dec`, const unsigned char packet[], `opus_int32` len)
- Gets the number of samples of an Opus packet.*
- void `opus_pcm_soft_clip` (float *pcm, int frame_size, int channels, float *softclip_mem)
- Applies soft-clipping to bring a float signal within the [-1,1] range.*
- int `opus_repacketizer_get_size` (void)
- Gets the size of an `OpusRepacketizer` structure.*
- `OpusRepacketizer * opus_repacketizer_init` (`OpusRepacketizer *rp`)
- (Re)initializes a previously allocated repacketizer state.*
- `OpusRepacketizer * opus_repacketizer_create` (void)
- Allocates memory and initializes the new repacketizer with `opus_repacketizer_init()`.*
- void `opus_repacketizer_destroy` (`OpusRepacketizer *rp`)
- Frees an `OpusRepacketizer` allocated by `opus_repacketizer_create()`.*
- int `opus_repacketizer_cat` (`OpusRepacketizer *rp`, const unsigned char *data, `opus_int32` len)
- Add a packet to the current repacketizer state.*
- `opus_int32 opus_repacketizer_out_range` (`OpusRepacketizer *rp`, int begin, int end, unsigned char *data, `opus_int32` maxlen)
- Construct a new packet from data previously submitted to the repacketizer state via `opus_repacketizer_cat()`.*
- int `opus_repacketizer_get_nb_frames` (`OpusRepacketizer *rp`)

Return the total number of frames contained in packet data submitted to the repacketizer state so far via `opus_repacketizer_cat()` since the last call to `opus_repacketizer_init()` or `opus_repacketizer_create()`.

- `opus_int32 opus_repacketizer_out` (`OpusRepacketizer *rp`, unsigned char *data, `opus_int32 maxlen`)
Construct a new packet from data previously submitted to the repacketizer state via `opus_repacketizer_cat()`.
- `int opus_packet_pad` (unsigned char *data, `opus_int32 len`, `opus_int32 new_len`)
Pads a given Opus packet to a larger size (possibly changing the TOC sequence).
- `opus_int32 opus_packet_unpad` (unsigned char *data, `opus_int32 len`)
Remove all padding from a given Opus packet and rewrite the TOC sequence to minimize space usage.
- `int opus_multistream_packet_pad` (unsigned char *data, `opus_int32 len`, `opus_int32 new_len`, `int nb_streams`)
Pads a given Opus multi-stream packet to a larger size (possibly changing the TOC sequence).
- `opus_int32 opus_multistream_packet_unpad` (unsigned char *data, `opus_int32 len`, `int nb_streams`)
Remove all padding from a given Opus multi-stream packet and rewrite the TOC sequence to minimize space usage.

5.1.1 Detailed Description

Opus reference implementation API.

5.2 opus_custom.h File Reference

Opus-Custom reference implementation API.

```
#include "opus_defines.h"
```

Macros

- `#define OPUS_CUSTOM_EXPORT`
- `#define OPUS_CUSTOM_EXPORT_STATIC`

Typedefs

- `typedef struct OpusCustomEncoder OpusCustomEncoder`
Contains the state of an encoder.
- `typedef struct OpusCustomDecoder OpusCustomDecoder`
State of the decoder.
- `typedef struct OpusCustomMode OpusCustomMode`
The mode contains all the information necessary to create an encoder.

Functions

- `OpusCustomMode * opus_custom_mode_create` (`opus_int32 Fs`, `int frame_size`, `int *error`)
Creates a new mode struct.
- `void opus_custom_mode_destroy` (`OpusCustomMode *mode`)
Destroys a mode struct.
- `int opus_custom_encoder_get_size` (`const OpusCustomMode *mode`, `int channels`)
Gets the size of an `OpusCustomEncoder` structure.

- `OpusCustomEncoder * opus_custom_encoder_create` (const `OpusCustomMode *mode`, int channels, int *error)
Creates a new encoder state.
- void `opus_custom_encoder_destroy` (`OpusCustomEncoder *st`)
Destroys a an encoder state.
- int `opus_custom_encode_float` (`OpusCustomEncoder *st`, const float *pcm, int frame_size, unsigned char *compressed, int maxCompressedBytes)
Encodes a frame of audio.
- int `opus_custom_encode` (`OpusCustomEncoder *st`, const `opus_int16 *pcm`, int frame_size, unsigned char *compressed, int maxCompressedBytes)
Encodes a frame of audio.
- int `opus_custom_encoder_ctl` (`OpusCustomEncoder *OPUS_RESTRICT st`, int request,...)
Perform a CTL function on an Opus custom encoder.
- int `opus_custom_decoder_get_size` (const `OpusCustomMode *mode`, int channels)
Gets the size of an OpusCustomDecoder structure.
- int `opus_custom_decoder_init` (`OpusCustomDecoder *st`, const `OpusCustomMode *mode`, int channels)
Initializes a previously allocated decoder state The memory pointed to by st must be the size returned by opus_custom_decoder_get_size.
- `OpusCustomDecoder * opus_custom_decoder_create` (const `OpusCustomMode *mode`, int channels, int *error)
Creates a new decoder state.
- void `opus_custom_decoder_destroy` (`OpusCustomDecoder *st`)
Destroys a an decoder state.
- int `opus_custom_decode_float` (`OpusCustomDecoder *st`, const unsigned char *data, int len, float *pcm, int frame_size)
Decode an opus custom frame with floating point output.
- int `opus_custom_decode` (`OpusCustomDecoder *st`, const unsigned char *data, int len, `opus_int16 *pcm`, int frame_size)
Decode an opus custom frame.
- int `opus_custom_decoder_ctl` (`OpusCustomDecoder *OPUS_RESTRICT st`, int request,...)
Perform a CTL function on an Opus custom decoder.

5.2.1 Detailed Description

Opus-Custom reference implementation API.

5.2.2 Macro Definition Documentation

5.2.2.1 `#define OPUS_CUSTOM_EXPORT`

5.2.2.2 `#define OPUS_CUSTOM_EXPORT_STATIC`

5.3 `opus_defines.h` File Reference

Opus reference implementation constants.

```
#include "opus_types.h"
```

Macros

- #define `OPUS_OK`
No error.
- #define `OPUS_BAD_ARG`
One or more invalid/out of range arguments.
- #define `OPUS_BUFFER_TOO_SMALL`
Not enough bytes allocated in the buffer.
- #define `OPUS_INTERNAL_ERROR`
An internal error was detected.
- #define `OPUS_INVALID_PACKET`
The compressed data passed is corrupted.
- #define `OPUS_UNIMPLEMENTED`
Invalid/unsupported request number.
- #define `OPUS_INVALID_STATE`
An encoder or decoder structure is invalid or already freed.
- #define `OPUS_ALLOC_FAIL`
Memory allocation has failed.
- #define `OPUS_AUTO`
Auto/default setting.
- #define `OPUS_BITRATE_MAX`
Maximum bitrate.
- #define `OPUS_APPLICATION_VOIP`
Best for most VoIP/videoconference applications where listening quality and intelligibility matter most.
- #define `OPUS_APPLICATION_AUDIO`
Best for broadcast/high-fidelity application where the decoded audio should be as close as possible to the input.
- #define `OPUS_APPLICATION_RESTRICTED_LOWDELAY`
Only use when lowest-achievable latency is what matters most.
- #define `OPUS_SIGNAL_VOICE` 3001
Signal being encoded is voice.
- #define `OPUS_SIGNAL_MUSIC` 3002
Signal being encoded is music.
- #define `OPUS_BANDWIDTH_NARROWBAND`
4 kHz bandpass
- #define `OPUS_BANDWIDTH_MEDIUMBAND`
6 kHz bandpass
- #define `OPUS_BANDWIDTH_WIDEBAND`
8 kHz bandpass
- #define `OPUS_BANDWIDTH_SUPERWIDEBAND`
12 kHz bandpass
- #define `OPUS_BANDWIDTH_FULLBAND`
20 kHz bandpass
- #define `OPUS_FRAME_SIZE_ARG` 5000
Select frame size from the argument (default)
- #define `OPUS_FRAME_SIZE_2_5_MS` 5001
Use 2.5 ms frames.
- #define `OPUS_FRAME_SIZE_5_MS` 5002

- *Use 5 ms frames.*
• #define OPUS_FRAMESIZE_10_MS 5003
- *Use 10 ms frames.*
• #define OPUS_FRAMESIZE_20_MS 5004
- *Use 20 ms frames.*
• #define OPUS_FRAMESIZE_40_MS 5005
- *Use 40 ms frames.*
• #define OPUS_FRAMESIZE_60_MS 5006
- *Use 60 ms frames.*
• #define OPUS_FRAMESIZE_80_MS 5007
- *Use 80 ms frames.*
• #define OPUS_FRAMESIZE_100_MS 5008
- *Use 100 ms frames.*
• #define OPUS_FRAMESIZE_120_MS 5009
- *Use 120 ms frames.*
• #define OPUS_SET_COMPLEXITY(x)
Configures the encoder's computational complexity.
- #define OPUS_GET_COMPLEXITY(x)
Gets the encoder's complexity configuration.
- #define OPUS_SET_BITRATE(x)
Configures the bitrate in the encoder.
- #define OPUS_GET_BITRATE(x)
Gets the encoder's bitrate configuration.
- #define OPUS_SET_VBR(x)
Enables or disables variable bitrate (VBR) in the encoder.
- #define OPUS_GET_VBR(x)
Determine if variable bitrate (VBR) is enabled in the encoder.
- #define OPUS_SET_VBR_CONSTRAINT(x)
Enables or disables constrained VBR in the encoder.
- #define OPUS_GET_VBR_CONSTRAINT(x)
Determine if constrained VBR is enabled in the encoder.
- #define OPUS_SET_FORCE_CHANNELS(x)
Configures mono/stereo forcing in the encoder.
- #define OPUS_GET_FORCE_CHANNELS(x)
Gets the encoder's forced channel configuration.
- #define OPUS_SET_MAX_BANDWIDTH(x)
Configures the maximum bandpass that the encoder will select automatically.
- #define OPUS_GET_MAX_BANDWIDTH(x)
Gets the encoder's configured maximum allowed bandpass.
- #define OPUS_SET_BANDWIDTH(x)
Sets the encoder's bandpass to a specific value.
- #define OPUS_SET_SIGNAL(x)
Configures the type of signal being encoded.
- #define OPUS_GET_SIGNAL(x)
Gets the encoder's configured signal type.
- #define OPUS_SET_APPLICATION(x)
Configures the encoder's intended application.

- #define `OPUS_GET_APPLICATION(x)`
Gets the encoder's configured application.
- #define `OPUS_GET_LOOKAHEAD(x)`
Gets the total samples of delay added by the entire codec.
- #define `OPUS_SET_INBAND_FEC(x)`
Configures the encoder's use of inband forward error correction (FEC).
- #define `OPUS_GET_INBAND_FEC(x)`
Gets encoder's configured use of inband forward error correction.
- #define `OPUS_SET_PACKET_LOSS_PERC(x)`
Configures the encoder's expected packet loss percentage.
- #define `OPUS_GET_PACKET_LOSS_PERC(x)`
Gets the encoder's configured packet loss percentage.
- #define `OPUS_SET_DTX(x)`
Configures the encoder's use of discontinuous transmission (DTX).
- #define `OPUS_GET_DTX(x)`
Gets encoder's configured use of discontinuous transmission.
- #define `OPUS_SET_LSB_DEPTH(x)`
Configures the depth of signal being encoded.
- #define `OPUS_GET_LSB_DEPTH(x)`
Gets the encoder's configured signal depth.
- #define `OPUS_SET_EXPERT_FRAME_DURATION(x)`
Configures the encoder's use of variable duration frames.
- #define `OPUS_GET_EXPERT_FRAME_DURATION(x)`
Gets the encoder's configured use of variable duration frames.
- #define `OPUS_SET_PREDICTION_DISABLED(x)`
If set to 1, disables almost all use of prediction, making frames almost completely independent.
- #define `OPUS_GET_PREDICTION_DISABLED(x)`
Gets the encoder's configured prediction status.
- #define `OPUS_RESET_STATE`
Resets the codec state to be equivalent to a freshly initialized state.
- #define `OPUS_GET_FINAL_RANGE(x)`
Gets the final state of the codec's entropy coder.
- #define `OPUS_GET_BANDWIDTH(x)`
Gets the encoder's configured bandpass or the decoder's last bandpass.
- #define `OPUS_GET_SAMPLE_RATE(x)`
Gets the sampling rate the encoder or decoder was initialized with.
- #define `OPUS_SET_PHASE_INVERSION_DISABLED(x)`
If set to 1, disables the use of phase inversion for intensity stereo, improving the quality of mono downmixes, but slightly reducing normal stereo quality.
- #define `OPUS_GET_PHASE_INVERSION_DISABLED(x)`
Gets the encoder's configured phase inversion status.
- #define `OPUS_SET_GAIN(x)`
Configures decoder gain adjustment.
- #define `OPUS_GET_GAIN(x)`
Gets the decoder's configured gain adjustment.
- #define `OPUS_GET_LAST_PACKET_DURATION(x)`
Gets the duration (in samples) of the last packet successfully decoded or concealed.
- #define `OPUS_GET_PITCH(x)`
Gets the pitch of the last decoded frame, if available.

Functions

- const char * [opus_strerror](#) (int error)
Converts an opus error code into a human readable string.
- const char * [opus_get_version_string](#) (void)
Gets the libopus version string.

5.3.1 Detailed Description

Opus reference implementation constants.

5.4 opus_multistream.h File Reference

Opus reference implementation multistream API.

```
#include "opus.h"
```

Macros

- #define [OPUS_MULTISTREAM_GET_ENCODER_STATE](#)(x, y)
Gets the encoder state for an individual stream of a multistream encoder.
- #define [OPUS_MULTISTREAM_GET_DECODER_STATE](#)(x, y)
Gets the decoder state for an individual stream of a multistream decoder.

Typedefs

- typedef struct [OpusMSEncoder](#) [OpusMSEncoder](#)
Opus multistream encoder state.
- typedef struct [OpusMSDecoder](#) [OpusMSDecoder](#)
Opus multistream decoder state.

Functions

Multistream encoder functions

- [opus_int32 opus_multistream_encoder_get_size](#) (int streams, int coupled_streams)
Gets the size of an OpusMSEncoder structure.
- [opus_int32 opus_multistream_surround_encoder_get_size](#) (int channels, int mapping_family)
- [OpusMSEncoder * opus_multistream_encoder_create](#) ([opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int application, int *error)
Allocates and initializes a multistream encoder state.
- [OpusMSEncoder * opus_multistream_surround_encoder_create](#) ([opus_int32](#) Fs, int channels, int mapping_family, int *streams, int *coupled_streams, unsigned char *mapping, int application, int *error)
- int [opus_multistream_encoder_init](#) ([OpusMSEncoder](#) *st, [opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int application)
Initialize a previously allocated multistream encoder state.
- int [opus_multistream_surround_encoder_init](#) ([OpusMSEncoder](#) *st, [opus_int32](#) Fs, int channels, int mapping_family, int *streams, int *coupled_streams, unsigned char *mapping, int application)

- int [opus_multistream_encode](#) ([OpusMSEncoder](#) *st, const [opus_int16](#) *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes a multistream Opus frame.
- int [opus_multistream_encode_float](#) ([OpusMSEncoder](#) *st, const float *pcm, int frame_size, unsigned char *data, [opus_int32](#) max_data_bytes)
Encodes a multistream Opus frame from floating point input.
- void [opus_multistream_encoder_destroy](#) ([OpusMSEncoder](#) *st)
Frees an [OpusMSEncoder](#) allocated by [opus_multistream_encoder_create\(\)](#).
- int [opus_multistream_encoder_ctl](#) ([OpusMSEncoder](#) *st, int request,...)
Perform a CTL function on a multistream Opus encoder.

Multistream decoder functions

- [opus_int32](#) [opus_multistream_decoder_get_size](#) (int streams, int coupled_streams)
Gets the size of an [OpusMSDecoder](#) structure.
- [OpusMSDecoder](#) * [opus_multistream_decoder_create](#) ([opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping, int *error)
Allocates and initializes a multistream decoder state.
- int [opus_multistream_decoder_init](#) ([OpusMSDecoder](#) *st, [opus_int32](#) Fs, int channels, int streams, int coupled_streams, const unsigned char *mapping)
Intialize a previously allocated decoder state object.
- int [opus_multistream_decode](#) ([OpusMSDecoder](#) *st, const unsigned char *data, [opus_int32](#) len, [opus_int16](#) *pcm, int frame_size, int decode_fec)
Decode a multistream Opus packet.
- int [opus_multistream_decode_float](#) ([OpusMSDecoder](#) *st, const unsigned char *data, [opus_int32](#) len, float *pcm, int frame_size, int decode_fec)
Decode a multistream Opus packet with floating point output.
- int [opus_multistream_decoder_ctl](#) ([OpusMSDecoder](#) *st, int request,...)
Perform a CTL function on a multistream Opus decoder.
- void [opus_multistream_decoder_destroy](#) ([OpusMSDecoder](#) *st)
Frees an [OpusMSDecoder](#) allocated by [opus_multistream_decoder_create\(\)](#).

5.4.1 Detailed Description

Opus reference implementation multistream API.

5.5 opus_types.h File Reference

Opus reference implementation types.

Macros

- #define [opus_int](#) int /* used for counters etc; at least 16 bits */
- #define [opus_int64](#) long long
- #define [opus_int8](#) signed char
- #define [opus_uint](#) unsigned int /* used for counters etc; at least 16 bits */
- #define [opus_uint64](#) unsigned long long
- #define [opus_uint8](#) unsigned char

Typedefs

- typedef short [opus_int16](#)
- typedef unsigned short [opus_uint16](#)
- typedef int [opus_int32](#)
- typedef unsigned int [opus_uint32](#)

5.5.1 Detailed Description

Opus reference implementation types.

5.5.2 Macro Definition Documentation

5.5.2.1 `#define opus_int int /* used for counters etc; at least 16 bits */`

5.5.2.2 `#define opus_int64 long long`

5.5.2.3 `#define opus_int8 signed char`

5.5.2.4 `#define opus_uint unsigned int /* used for counters etc; at least 16 bits */`

5.5.2.5 `#define opus_uint64 unsigned long long`

5.5.2.6 `#define opus_uint8 unsigned char`

5.5.3 Typedef Documentation

5.5.3.1 `typedef short opus_int16`

5.5.3.2 `typedef int opus_int32`

5.5.3.3 `typedef unsigned short opus_uint16`

5.5.3.4 `typedef unsigned int opus_uint32`

Index

- Decoder related CTLs, [51](#)
 - [OPUS_GET_GAIN](#), [51](#)
 - [OPUS_GET_PITCH](#), [51](#)
 - [OPUS_SET_GAIN](#), [52](#)
- Encoder related CTLs, [35](#)
 - [OPUS_GET_BITRATE](#), [37](#)
 - [OPUS_GET_DTX](#), [37](#)
 - [OPUS_GET_LOOKAHEAD](#), [39](#)
 - [OPUS_GET_SIGNAL](#), [40](#)
 - [OPUS_GET_VBR](#), [41](#)
 - [OPUS_SET_BANDWIDTH](#), [42](#)
 - [OPUS_SET_BITRATE](#), [42](#)
 - [OPUS_SET_DTX](#), [43](#)
 - [OPUS_SET_SIGNAL](#), [46](#)
 - [OPUS_SET_VBR](#), [46](#)
- Error codes, [29](#)
 - [OPUS_ALLOC_FAIL](#), [29](#)
 - [OPUS_BAD_ARG](#), [29](#)
 - [OPUS_INTERNAL_ERROR](#), [29](#)
 - [OPUS_INVALID_PACKET](#), [29](#)
 - [OPUS_INVALID_STATE](#), [29](#)
 - [OPUS_OK](#), [30](#)
 - [OPUS_UNIMPLEMENTED](#), [30](#)
- Generic CTLs, [48](#)
 - [OPUS_GET_BANDWIDTH](#), [48](#)
 - [OPUS_RESET_STATE](#), [50](#)
- Multistream specific encoder and decoder CTLs, [54](#)
- [OPUS_ALLOC_FAIL](#)
 - Error codes, [29](#)
- [OPUS_AUTO](#)
 - Pre-defined values for CTL interface, [32](#)
- [OPUS_BAD_ARG](#)
 - Error codes, [29](#)
- [OPUS_BITRATE_MAX](#)
 - Pre-defined values for CTL interface, [32](#)
- [OPUS_CUSTOM_EXPORT](#)
 - [opus_custom.h](#), [76](#)
- [OPUS_FRAME_SIZE_ARG](#)
 - Pre-defined values for CTL interface, [33](#)
- [OPUS_GET_BANDWIDTH](#)
 - Generic CTLs, [48](#)
- [OPUS_GET_BITRATE](#)
 - Encoder related CTLs, [37](#)
- [OPUS_GET_COMPLEXITY](#)
 - Encoder related CTLs, [37](#)
- [OPUS_GET_DTX](#)
 - Encoder related CTLs, [37](#)
- [OPUS_GET_GAIN](#)
 - Decoder related CTLs, [51](#)
- [OPUS_GET_LOOKAHEAD](#)
 - Encoder related CTLs, [39](#)
- [OPUS_GET_LSB_DEPTH](#)
 - Encoder related CTLs, [39](#)
- [OPUS_GET_PITCH](#)
 - Decoder related CTLs, [51](#)
- [OPUS_GET_SIGNAL](#)
 - Encoder related CTLs, [40](#)
- [OPUS_GET_VBR](#)
 - Encoder related CTLs, [41](#)
- [OPUS_INTERNAL_ERROR](#)
 - Error codes, [29](#)
- [OPUS_INVALID_PACKET](#)
 - Error codes, [29](#)
- [OPUS_INVALID_STATE](#)
 - Error codes, [29](#)
- [OPUS_OK](#)
 - Error codes, [30](#)
- [OPUS_RESET_STATE](#)
 - Generic CTLs, [50](#)
- [OPUS_SET_BANDWIDTH](#)
 - Encoder related CTLs, [42](#)
- [OPUS_SET_BITRATE](#)
 - Encoder related CTLs, [42](#)
- [OPUS_SET_COMPLEXITY](#)
 - Encoder related CTLs, [43](#)
- [OPUS_SET_DTX](#)
 - Encoder related CTLs, [43](#)
- [OPUS_SET_GAIN](#)
 - Decoder related CTLs, [52](#)
- [OPUS_SET_LSB_DEPTH](#)
 - Encoder related CTLs, [45](#)
- [OPUS_SET_SIGNAL](#)
 - Encoder related CTLs, [46](#)
- [OPUS_SET_VBR](#)
 - Encoder related CTLs, [46](#)
- [OPUS_SIGNAL_MUSIC](#)
 - Pre-defined values for CTL interface, [33](#)

- OPUS_SIGNAL_VOICE
 - Pre-defined values for CTL interface, 34
- OPUS_UNIMPLEMENTED
 - Error codes, 30
- Opus Custom, 66
 - opus_custom_decode, 68
 - opus_custom_decode_float, 68
 - opus_custom_decoder_create, 68
 - opus_custom_decoder_ctl, 69
 - opus_custom_decoder_destroy, 69
 - opus_custom_decoder_get_size, 69
 - opus_custom_decoder_init, 69
 - opus_custom_encode, 70
 - opus_custom_encode_float, 70
 - opus_custom_encoder_create, 70
 - opus_custom_encoder_ctl, 71
 - opus_custom_encoder_destroy, 71
 - opus_custom_encoder_get_size, 71
 - opus_custom_mode_create, 71
 - opus_custom_mode_destroy, 72
 - OpusCustomDecoder, 67
 - OpusCustomEncoder, 67
 - OpusCustomMode, 67
- Opus Decoder, 13
 - opus_decode, 15
 - opus_decode_float, 15
 - opus_decoder_create, 16
 - opus_decoder_ctl, 16
 - opus_decoder_destroy, 16
 - opus_decoder_get_nb_samples, 17
 - opus_decoder_get_size, 17
 - opus_decoder_init, 17
 - opus_packet_get_bandwidth, 18
 - opus_packet_get_nb_channels, 18
 - opus_packet_get_nb_frames, 18
 - opus_packet_get_nb_samples, 19
 - opus_packet_get_samples_per_frame, 19
 - opus_packet_parse, 19
 - opus_pcm_soft_clip, 20
 - OpusDecoder, 15
- Opus Encoder, 7
 - opus_encode, 9
 - opus_encode_float, 10
 - opus_encoder_create, 10
 - opus_encoder_ctl, 11
 - opus_encoder_destroy, 11
 - opus_encoder_get_size, 11
 - opus_encoder_init, 11
 - OpusEncoder, 9
- Opus library information functions, 53
 - opus_get_version_string, 53
 - opus_strerror, 53
- Opus Multistream API, 56
 - opus_multistream_decode, 58
 - opus_multistream_decode_float, 58
 - opus_multistream_decoder_create, 59
 - opus_multistream_decoder_ctl, 59
 - opus_multistream_decoder_destroy, 60
 - opus_multistream_decoder_get_size, 60
 - opus_multistream_decoder_init, 60
 - opus_multistream_encode, 61
 - opus_multistream_encode_float, 62
 - opus_multistream_encoder_create, 62
 - opus_multistream_encoder_ctl, 63
 - opus_multistream_encoder_destroy, 63
 - opus_multistream_encoder_get_size, 63
 - opus_multistream_encoder_init, 64
 - opus_multistream_surround_encoder_create, 64
 - opus_multistream_surround_encoder_get_size, 64
 - opus_multistream_surround_encoder_init, 64
 - OpusMSDecoder, 57
 - OpusMSEncoder, 58
- opus.h, 73
- opus_custom.h, 75
- opus_custom_decode
 - Opus Custom, 68
- opus_custom_decode_float
 - Opus Custom, 68
- opus_custom_decoder_create
 - Opus Custom, 68
- opus_custom_decoder_ctl
 - Opus Custom, 69
- opus_custom_decoder_destroy
 - Opus Custom, 69
- opus_custom_decoder_get_size
 - Opus Custom, 69
- opus_custom_decoder_init
 - Opus Custom, 69
- opus_custom_encode
 - Opus Custom, 70
- opus_custom_encode_float
 - Opus Custom, 70
- opus_custom_encoder_create
 - Opus Custom, 70
- opus_custom_encoder_ctl
 - Opus Custom, 71
- opus_custom_encoder_destroy
 - Opus Custom, 71
- opus_custom_encoder_get_size
 - Opus Custom, 71
- opus_custom_mode_create
 - Opus Custom, 71
- opus_custom_mode_destroy
 - Opus Custom, 72
- opus_decode
 - Opus Decoder, 15
- opus_decode_float
 - Opus Decoder, 15

- opus_decoder_create
 - Opus Decoder, [16](#)
- opus_decoder_ctl
 - Opus Decoder, [16](#)
- opus_decoder_destroy
 - Opus Decoder, [16](#)
- opus_decoder_get_nb_samples
 - Opus Decoder, [17](#)
- opus_decoder_get_size
 - Opus Decoder, [17](#)
- opus_decoder_init
 - Opus Decoder, [17](#)
- opus_defines.h, [76](#)
- opus_encode
 - Opus Encoder, [9](#)
- opus_encode_float
 - Opus Encoder, [10](#)
- opus_encoder_create
 - Opus Encoder, [10](#)
- opus_encoder_ctl
 - Opus Encoder, [11](#)
- opus_encoder_destroy
 - Opus Encoder, [11](#)
- opus_encoder_get_size
 - Opus Encoder, [11](#)
- opus_encoder_init
 - Opus Encoder, [11](#)
- opus_get_version_string
 - Opus library information functions, [53](#)
- opus_int
 - opus_types.h, [82](#)
- opus_int16
 - opus_types.h, [82](#)
- opus_int32
 - opus_types.h, [82](#)
- opus_int64
 - opus_types.h, [82](#)
- opus_int8
 - opus_types.h, [82](#)
- opus_multistream.h, [80](#)
- opus_multistream_decode
 - Opus Multistream API, [58](#)
- opus_multistream_decode_float
 - Opus Multistream API, [58](#)
- opus_multistream_decoder_create
 - Opus Multistream API, [59](#)
- opus_multistream_decoder_ctl
 - Opus Multistream API, [59](#)
- opus_multistream_decoder_destroy
 - Opus Multistream API, [60](#)
- opus_multistream_decoder_get_size
 - Opus Multistream API, [60](#)
- opus_multistream_decoder_init
 - Opus Multistream API, [60](#)
- opus_multistream_encode
 - Opus Multistream API, [61](#)
- opus_multistream_encode_float
 - Opus Multistream API, [62](#)
- opus_multistream_encoder_create
 - Opus Multistream API, [62](#)
- opus_multistream_encoder_ctl
 - Opus Multistream API, [63](#)
- opus_multistream_encoder_destroy
 - Opus Multistream API, [63](#)
- opus_multistream_encoder_get_size
 - Opus Multistream API, [63](#)
- opus_multistream_encoder_init
 - Opus Multistream API, [64](#)
- opus_multistream_packet_pad
 - Repacketizer, [23](#)
- opus_multistream_packet_unpad
 - Repacketizer, [24](#)
- opus_multistream_surround_encoder_create
 - Opus Multistream API, [64](#)
- opus_multistream_surround_encoder_get_size
 - Opus Multistream API, [64](#)
- opus_multistream_surround_encoder_init
 - Opus Multistream API, [64](#)
- opus_packet_get_bandwidth
 - Opus Decoder, [18](#)
- opus_packet_get_nb_channels
 - Opus Decoder, [18](#)
- opus_packet_get_nb_frames
 - Opus Decoder, [18](#)
- opus_packet_get_nb_samples
 - Opus Decoder, [19](#)
- opus_packet_get_samples_per_frame
 - Opus Decoder, [19](#)
- opus_packet_pad
 - Repacketizer, [24](#)
- opus_packet_parse
 - Opus Decoder, [19](#)
- opus_packet_unpad
 - Repacketizer, [25](#)
- opus_pcm_soft_clip
 - Opus Decoder, [20](#)
- opus_repacketizer_cat
 - Repacketizer, [25](#)
- opus_repacketizer_create
 - Repacketizer, [26](#)
- opus_repacketizer_destroy
 - Repacketizer, [26](#)
- opus_repacketizer_get_nb_frames
 - Repacketizer, [26](#)
- opus_repacketizer_get_size
 - Repacketizer, [26](#)
- opus_repacketizer_init
 - Repacketizer, [26](#)

- opus_repacketizer_out
 - Repacketizer, [27](#)
- opus_repacketizer_out_range
 - Repacketizer, [28](#)
- opus_strerror
 - Opus library information functions, [53](#)
- opus_types.h, [81](#)
 - opus_int, [82](#)
 - opus_int16, [82](#)
 - opus_int32, [82](#)
 - opus_int64, [82](#)
 - opus_int8, [82](#)
 - opus_uint, [82](#)
 - opus_uint16, [82](#)
 - opus_uint32, [82](#)
 - opus_uint64, [82](#)
 - opus_uint8, [82](#)
- opus_uint
 - opus_types.h, [82](#)
- opus_uint16
 - opus_types.h, [82](#)
- opus_uint32
 - opus_types.h, [82](#)
- opus_uint64
 - opus_types.h, [82](#)
- opus_uint8
 - opus_types.h, [82](#)
- OpusCustomDecoder
 - Opus Custom, [67](#)
- OpusCustomEncoder
 - Opus Custom, [67](#)
- OpusCustomMode
 - Opus Custom, [67](#)
- OpusDecoder
 - Opus Decoder, [15](#)
- OpusEncoder
 - Opus Encoder, [9](#)
- OpusMSDecoder
 - Opus Multistream API, [57](#)
- OpusMSEncoder
 - Opus Multistream API, [58](#)
- OpusRepacketizer
 - Repacketizer, [23](#)
- Pre-defined values for CTL interface, [31](#)
 - OPUS_AUTO, [32](#)
 - OPUS_BITRATE_MAX, [32](#)
 - OPUS_SIGNAL_MUSIC, [33](#)
 - OPUS_SIGNAL_VOICE, [34](#)
- Repacketizer, [21](#)
 - opus_multistream_packet_pad, [23](#)
 - opus_multistream_packet_unpad, [24](#)
 - opus_packet_pad, [24](#)
 - opus_packet_unpad, [25](#)
- opus_repacketizer_cat, [25](#)
- opus_repacketizer_create, [26](#)
- opus_repacketizer_destroy, [26](#)
- opus_repacketizer_get_nb_frames, [26](#)
- opus_repacketizer_get_size, [26](#)
- opus_repacketizer_init, [26](#)
- opus_repacketizer_out, [27](#)
- opus_repacketizer_out_range, [28](#)
- OpusRepacketizer, [23](#)